arXiv:1504.04432v1 [cs.IT] 17 Apr 2015

On the Cost and Benefit of Cooperation (Extended Version)

Parham Noorzad
California Institute of Technology
parham@caltech.edu

Michelle Effros
California Institute of Technology
effros@caltech.edu

Michael Langberg
State University of New York at Buffalo
mikel@buffalo.edu

***Abstract*—In a cooperative coding scheme, network nodes work together to achieve higher transmission rates. To obtain a better understanding of cooperation, we consider a model in which two transmitters send rate-limited descriptions of their messages to a "cooperation facilitator", a node that sends back rate-limited descriptions of the pair to each transmitter. This model includes the conferencing encoders model and a prior model from the current authors as special cases. We show that except for a special class of multiple access channels, the gain in sum-capacity resulting from cooperation under this model is quite large. Adding a cooperation facilitator to any such channel results in a network that does not satisfy the edge removal property. An important special case is the Gaussian multiple access channel, for which we explicitly characterize the sum-rate cooperation gain.**

I. INTRODUCTION

To meet the growing demand for higher transmission rates, network nodes should employ coding schemes that use scarce resources in a more efficient manner. By working together, network nodes can take advantage of under-utilized network resources to help data transmisssion in heavily constrained regions of the network. Cooperation among nodes emerges as a natural strategy towards this aim.

We propose a network model and use it to study the cost and benefit of enabling a cooperation in a given network. As an example, consider two nodes, A and B, transmitting independent messages over a network $\mathcal{N}$. A third node C that has bidirectional links to A and B can help A and B work together to achieve a higher sum-rate than they would have achieved had they worked separately.

We seek to understand how the gain in sum-rate resulting from cooperation between A and B relates to the capacities of the links from (A, B) to C and back. Intuitively, we think of the increase in sum-rate as the *benefit* of cooperation and the capacities of the links between (A, B) and C as the *cost* of cooperation. See Figure 1.



Figure 1. An example of cooperation among network nodes. Node C enables nodes A and B to cooperate and potentially achieve higher rates in the transmission of their messages over network $\mathcal{N}$.

To study this situation formally, let A and B be the encoders of a memoryless multiple access channel (MAC). Let C be a "cooperation facilitator" (CF), a node which, prior to the transmission of the messages over the network, receives a rate-limited description of each encoder's message and sends a rate-limited output to each encoder. See Figure 2.

In *one-step cooperation*, each encoder sends a function of its message to the CF and the CF transmits, to each encoder, a value that is a function of both of its inputs. Similarly, we can define *k-step cooperation* (for a fixed positive integer k) between the CF and the encoders where the information transmission between the CF and each encoder continues for k steps, with the constraint that the information that the CF or each encoder transmits in each step only depends on the information that it previously received. In our achievability result, however, we only use one-step cooperation for simplicity.

Our CF extends the cooperation model introduced by a previous work of the authors [1] to allow for rate-limited inputs. While the CF in [1] has full knowledge of both messages and transmits a rate-limited output to both encoders, the more general CF we study in this paper only has partial knowledge of each encoder's message. In addition, unlike in [1], we allow the CF to send a different output to each encoder. We define our cooperation model formally in Section II.

The main result of [1] states that there exists a discrete memoryless MAC where encoder cooperation through a CF results in a large gain (with respect to the capacities of the output edges of the CF). This implies the existence of a network consisting of a MAC with a CF that does not satisfy the "edge removal property" [2], [3]. We say a network satisfies the edge removal property if removing an edge from that network does not reduce the achievable rate of any of the source messages by more than the capacity of that edge. A question that remained unanswered in [1] was whether such a result is true for more natural channels, e.g., the Gaussian MAC. The answer turns out to be positive, and except for a special class of MACs, adding a CF results in a large sum-capacity gain (Theorem 1).

Our achievability scheme combines three coding schemes via rate splitting. First, each encoder sends part of its message to the CF. The CF passes on part of what it receives from each encoder to the other encoder without any further operations. In this way the CF enables "conferencing" between the encoders, which is a cooperation strategy introduced by Willems [4].

The CF uses the remaining part of what it receives to help



Figure 2. The network model for the MAC with a CF.

the encoders "coordinate" their transmissions; that is, it enables the encoders to create dependence among independently generated codewords. For this coordination strategy, we rely on results from rate-distortion theory [5, pp. 318-324], which were used by Marton [6] and El Gamal and Van der Meulen [7] to obtain an inner bound for the capacity region of the broadcast channel.

Finally, for the remaining part of the messages, which do not go through the CF, the encoders use the classical coding scheme of Ahlswede [8], [9] and Liao [10]. We formally introduce our achievable scheme in Section III, and study its performance in Section IV.

In Section V we provide an inner bound for the Gaussian MAC with transmitter cooperation using methods similar to [11]. We compare the sum-rate gain of our inner bound with the sum-rate gain of schemes that use only one or another of our strategies. We see that none alone performs as well as their combination, which is the scheme we propose here.

II. THE COOPERATION MODEL

Let $(\mathcal{X}_1 \times \mathcal{X}_2, P(y|x_1, x_2), \mathcal{Y})$ denote a memoryless MAC. Suppose W_1 and W_2 are the messages that encoders 1 and 2 transmit, respectively. For every positive integer k, define $[k] = \{1, \ldots, k\}$. We assume that W_1 and W_2 are independent and uniformly distributed over the sets $[M_1]$ and $[M_2]$, respectively.

For $i = 1, 2$, represent encoder i by the mappings

$$\begin{aligned} \varphi_i &: [M_i] \to \left[2^{nC_i^{\text{in}}}\right] \\ f_i &: [M_i] \times \left[2^{nC_i^{\text{out}}}\right] \to \mathcal{X}_i^n \end{aligned}$$

that describe the transmissions to the CF and channel, respectively. We represent the CF by the mappings

$$\psi_i : \left[2^{nC_1^{\text{in}}}\right] \times \left[2^{nC_2^{\text{in}}}\right] \to \left[2^{nC_i^{\text{out}}}\right],$$

where ψ_i denotes the output of the CF to encoder i for $i = 1, 2$. Under this definition, when $(W_1, W_2) = (w_1, w_2)$, the CF receives $\varphi_1(w_1)$ and $\varphi_2(w_2)$ from encoders 1 and 2, respectively. The CF then sends $\psi_1(\varphi_1(w_1), \varphi_2(w_2))$ to encoder 1 and $\psi_2(\varphi_1(w_1), \varphi_2(w_2))$ to encoder 2.

We represent the decoder by the mapping

$$g : \mathcal{Y}^n \to [M_1] \times [M_2].$$

Then the probability of error is given by

$$P_e^{(n)} = \mathbf{P}\left\{g(Y^n) \neq (W_1, W_2)\right\}.$$

Define $\mathbf{C}^{\text{in}} = (C_1^{\text{in}}, C_2^{\text{in}})$ and $\mathbf{C}^{\text{out}} = (C_1^{\text{out}}, C_2^{\text{out}})$. We call the mappings $(\varphi_1, \varphi_2, \psi_1, \psi_2, f_1, f_2, g)$ an (n, M_1, M_2) code for the MAC with a $(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$-CF. For nonnegative real numbers R_1 and R_2, we say that the rate pair (R_1, R_2) is achievable if for every $\epsilon > 0$ and sufficiently large n, there exists an (n, M_1, M_2) code such that $P_e^{(n)} \leq \epsilon$ and

$$\frac{1}{n} \log M_i > R_i - \epsilon,$$

for $i = 1, 2$. We define the capacity region as the closure of the set of all achievable rate pairs (R_1, R_2) and denote it by $\mathscr{C}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$.

Using the capacity region of the MAC with conferencing encoders [4] (Appendix A), we obtain inner and outer bounds for the capacity region of a MAC with a CF. Let $\mathscr{C}_{\text{conf}}(C_{12}, C_{21})$ denote the capacity region of a MAC with a (C_{12}, C_{21}) conference. Since the conferencing capacity region can be achieved with a single step of conferencing [4], it follows that

$$\mathscr{C}_{\text{conf}}\big(\min\{C_1^{\text{in}}, C_2^{\text{out}}\}, \min\{C_2^{\text{in}}, C_1^{\text{out}}\}\big)$$

is an inner bound for $\mathscr{C}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$. In addition, since each encoder could calculate the CF output if it only knew what the CF received from the other encoder, $\mathscr{C}_{\text{conf}}(C_1^{\text{in}}, C_2^{\text{in}})$ is an outer bound for $\mathscr{C}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$. We henceforth refer to these inner and outer bounds as the *conferencing bounds*. Note that when $C_2^{\text{out}} \geq C_1^{\text{in}}$ and $C_1^{\text{out}} \geq C_2^{\text{in}}$, the conferencing inner and outer bounds agree, giving

$$\mathscr{C}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}}) = \mathscr{C}_{\text{conf}}(C_1^{\text{in}}, C_2^{\text{in}}).$$

We next discuss the main result of this paper. For any memoryless MAC $(\mathcal{X}_1 \times \mathcal{X}_2, P(y|x_1, x_2), \mathcal{Y})$ with a $(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$-CF, define the sum-capacity as

$$C_{\text{sum}} = \max_{\mathscr{C}(\mathbf{C}_{\text{in}}, \mathbf{C}_{\text{out}})} (R_1 + R_2).$$

For a fixed $\mathbf{C}_{\text{in}}$ with $\min\{C_1^{\text{in}}, C_2^{\text{in}}\} > 0$, define the "sum-capacity gain" $G : \mathbb{R}_{\geq 0} \to \mathbb{R}_{\geq 0}$ as

$$G(C_{\text{out}}) = C_{\text{sum}}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}}) - C_{\text{sum}}(\mathbf{C}^{\text{in}}, \mathbf{0}),$$

where $\mathbf{C}_{\text{out}} = (C_{\text{out}}, C_{\text{out}})$ and $\mathbf{0} = (0, 0)$. Note that when $C_{\text{out}} = 0$, no cooperation is possible, thus

$$C_{\text{sum}}(\mathbf{C}^{\text{in}}, \mathbf{0}) = \max_{P(x_1)P(x_2)} I(X_1, X_2; Y).$$

The next theorem states that for any MAC where using dependent codewords (instead of independent ones) results in an increase in sum-capacity, the effect of cooperation through a CF can be quite large. In particular, it shows that the network consisting of any such MAC and a CF does not satisfy the edge removal property [2], [3].

Theorem 1 (Sum-capacity)**.** *For any discrete memoryless MAC $(\mathcal{X}_1 \times \mathcal{X}_2, P(y|x_1, x_2), \mathcal{Y})$ that satisfies*

$$\max_{P(x_1, x_2)} I(X_1, X_2; Y) > \max_{P(x_1)P(x_2)} I(X_1, X_2; Y),$$

we have $G'(0) = \infty$. For the Gaussian MAC, a stronger result holds: For some positive constant α and sufficiently small C_{out},

$$G(C_{\text{out}}) \geq \alpha\sqrt{C_{\text{out}}},$$

The proof of Theorem 1 (Appendix B), is based on our achievability result for the MAC with a CF, which we next describe. Define

$$\mathscr{R}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$$

as the set of all rate pairs (R_1, R_2) that for $(i,j) \in \{(1,2),(2,1)\}$ satisfy

$$\begin{aligned}
R_i &< I(X_i;Y|U,V_1,V_2,X_j) + C_i^{\text{in}}\\
R_i &< I(X_i;Y|U,V_j,X_j) + C_{i0}\\
R_1 + R_2 &< I(X_1,X_2;Y|U,V_1,V_2) + C_1^{\text{in}} + C_2^{\text{in}}\\
R_1 + R_2 &< I(X_1,X_2;Y|U,V_i) + C_i^{\text{in}} + C_{j0}\\
R_1 + R_2 &< I(X_1,X_2;Y|U) + C_{10} + C_{20}\\
R_1 + R_2 &< I(X_1,X_2;Y),
\end{aligned}$$

for nonnegative constants C_{10} and C_{20}, and distributions $P(u,v_1,v_2)P(x_1|u,v_1)P(x_2|u,v_2)$ that satisfy

$$\begin{aligned}
C_{i0} &\leq \min\left\{C_i^{\text{in}}, C_j^{\text{out}}\right\} \qquad (1)\\
I(V_1;V_2|U) &\leq (C_1^{\text{out}} - C_{20}) + (C_2^{\text{out}} - C_{10}).
\end{aligned}$$

In the above definition, the pair (U, V_i) represents the information encoder i receives from the CF. In addition, the pair (C_{10}, C_{20}) indicates the amount of rate being used on the CF links to enable the conferencing strategy. The remaining part of rate on the CF links is used to create dependence between V_1 and V_2.

Theorem 2 (Achievability)**.** *For any memoryless MAC* $(\mathcal{X}_1 \times \mathcal{X}_2, P(y|x_1,x_2), \mathcal{Y})$ *with a* $(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$*-CF, the rate region* $\mathscr{R}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$ *is achievable.*

A nontrivial special case is the case where the CF has complete knowledge of both source messages, that is, $C_1^{\text{in}} = C_2^{\text{in}} = \infty$. In this case, it is not hard to see (Appendix C) that $\mathscr{R}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$ simplifies to the set of all nonnegative rate pairs (R_1, R_2) that satisfy

$$\begin{aligned}
R_1 &< I(X_1;Y|U,X_2) + C_{10}\\
R_2 &< I(X_2;Y|U,X_1) + C_{20}\\
R_1 + R_2 &< I(X_1,X_2;Y|U) + C_{10} + C_{20}\\
R_1 + R_2 &< I(X_1,X_2;Y),
\end{aligned}$$

for nonnegative constants $C_{10} \leq C_2^{\text{out}}$ and $C_{20} \leq C_1^{\text{out}}$, and distributions $P(u,x_1,x_2)$ with

$$I(X_1;X_2|U) \leq (C_1^{\text{out}} - C_{20}) + (C_2^{\text{out}} - C_{10}).$$

Note that in this case, increasing the number of cooperation steps (Section I) does not change the family of functions the CF can compute. Thus as with the case where $C_1^{\text{in}} \leq C_2^{\text{out}}$ and $C_2^{\text{in}} \leq C_1^{\text{out}}$, using more than one step for cooperation does not enlarge the capacity region.

The rate region, $\mathscr{R}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$, in addition to being achievable, is also convex. To prove this, we show a slightly stronger result. For every $\lambda \in (0,1)$, $(\mathbf{C}_a^{\text{in}}, \mathbf{C}_a^{\text{out}})$, and $(\mathbf{C}_b^{\text{in}}, \mathbf{C}_b^{\text{out}})$, define

$$\mathscr{R}_\lambda = \mathscr{R}\big(\lambda \mathbf{C}_a^{\text{in}} + (1-\lambda)\mathbf{C}_b^{\text{in}}, \lambda \mathbf{C}_a^{\text{out}} + (1-\lambda)\mathbf{C}_b^{\text{out}}\big).$$

Also define $\mathscr{R}_a = \mathscr{R}(\mathbf{C}_a^{\text{in}}, \mathbf{C}_a^{\text{out}})$ and $\mathscr{R}_b = \mathscr{R}(\mathbf{C}_b^{\text{in}}, \mathbf{C}_b^{\text{out}})$. We then have the following result.

Theorem 3 (Convexity)**.** *For any* $\lambda \in (0,1)$,

$$\mathscr{R}_\lambda \supseteq \lambda \mathscr{R}_a + (1-\lambda)\mathscr{R}_b.$$

The addition in Theorem 3 is the Minkowski sum [12], defined for any two subsets A and B of $\mathbb{R}^2$ as

$$A + B = \big\{(a_1 + b_1, a_2 + b_2) | (a_1,a_2) \in A, (b_1,b_2) \in B\big\}.$$

If we set $\mathbf{C}_a^{\text{in}} = \mathbf{C}_b^{\text{in}}$ and $\mathbf{C}_a^{\text{out}} = \mathbf{C}_b^{\text{out}}$ in Theorem 3 we get $\mathscr{R} \supseteq \lambda\mathscr{R} + (1-\lambda)\mathscr{R}$, which is equivalent to the convexity of $\mathscr{R}$. Using a time-sharing argument, we see that the capacity region $\mathscr{C}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$ also satisfies the property stated in Theorem 3. We prove Theorem 3 in Appendix D using techniques from the work of Cover, El Gamal, and Salehi [13].

III. The Achievability Scheme

In this section, we give a formal description of our coding scheme. First, pick nonnegative constants C_{10} and C_{20} such that Equation (1) holds for $\{i,j\} = \{1,2\}$. In our achievability scheme, the first nC_{i0} bits of W_i are sent directly from encoder i to encoder j through the CF without any modification. We thus require C_{i0} to satisfy inequality (1).

Next, choose C_{1d} and C_{2d} such that

$$\begin{aligned}
C_{1d} &\leq C_1^{\text{out}} - C_{20}\\
C_{2d} &\leq C_2^{\text{out}} - C_{10}.
\end{aligned} \qquad (2)$$

The values of C_{1d} and C_{2d} specify the amount of rate used on each of the output links for the coordination strategy. Finally, choose an input distribution $P(u,v_1,v_2)P(x_1|u,v_1)P(x_2|u,v_2)$ so that $P(u,v_1,v_2)$ satisfies

$$\zeta := C_{1d} + C_{2d} - I(V_1;V_2|U) > 0. \qquad (3)$$

Fix $\epsilon > 0$. Let $A_\epsilon^{(n)}$ be the weakly typical set [5, p. 521] with respect to the distribution

$$P(u,v_1,v_2)P(x_1|u,v_1)P(x_2|u,v_2)P(y|x_1,x_2).$$

By Cramér's large deviation theorem [14, p. 27], there exists a nondecreasing function $\Theta : \mathbb{R}^+ \to \mathbb{R}^+$ such that

$$\mathbf{P}\left\{\left(A_\epsilon^{(n)}\right)^c\right\} \leq 2^{-n\Theta(\epsilon)}. \qquad (4)$$

Fix $\delta > 0$ and let $A_\delta^{(n)}$ denote the weakly typical set with respect to $P(u,v_1,v_2)$. We make use of the typical sets $A_\delta^{(n)}$ and $A_\epsilon^{(n)}$ in the encoding and decoding processes, respectively.

We next describe the codebook generation. For $i = 1,2$, let $M_i = \lfloor 2^{nR_i} \rfloor$ and define $R_{i0} = \min\{R_i, C_{i0}\}$, $R_{id} = \min\{R_i, C_i^{\text{in}}\} - R_{i0}$, and $R_{ii} = (R_i - C_i^{\text{in}})^+$, where for any real number x, $x^+ = \max\{x, 0\}$. Note that for $i = 1,2$, $R_i = R_{i0} + R_{id} + R_{ii}$, thus we can split each of the messages into three parts as

$$W_i = (W_{i0}, W_{id}, W_{ii}) \in \left[2^{nR_{i0}}\right] \times \left[2^{nR_{id}}\right] \times \left[2^{nR_{ii}}\right].$$

Here W_{10} and W_{20} are used for conferencing, W_{1d} and W_{2d} are used for coordination, and W_{11} and W_{22} are transmitted over the channel independently.

Next, for every $(w_{10}, w_{20}) \in [2^{n(R_{10}+R_{20})}]$, generate $U^n(w_{10}, w_{20})$ i.i.d. with the distribution

$$\mathbf{P}\left\{U^n(w_{10}, w_{20}) = u^n\right\} = \prod_{t=1}^{n} P(u_t).$$

Let $E(u^n)$ be the event $\{U^n(w_{10}, w_{20}) = u^n\}$. Given $E(u^n)$, for every $(w_{id}, z_i) \in [2^{nR_{id}}] \times [2^{nC_{id}}]$, generate $V_i^n(w_{id}, z_i|u^n)$ according to

$$\mathbf{P}\left\{V_i^n(w_{id}, z_i|u^n) = v_i^n \middle| E(u^n)\right\} = \prod_{t=1}^{n} P(v_{it}|u_t),$$

for $i = 1, 2$, where $P(v_1|u)$ and $P(v_2|u)$ are marginals of $P(v_1, v_2|u)$.

Fix $(w_{10}, w_{20}, w_{1d}, w_{2d})$ and functions

$$\nu_i : \left[2^{nC_{id}}\right] \to \mathcal{V}_i^n$$

for $i = 1, 2$. Let $E(u^n, \nu_1, \nu_2)$ denote the event where $U^n(w_{10}, w_{20}) = u^n$ and $V_1^n(w_{1d}, .|u^n) = \nu_1(.)$, and $V_2^n(w_{2d}, .|u^n) = \nu_2(.)$. In addition, for any u^n, ν_1, and ν_2, define the set

$$\mathcal{A}(u^n, \nu_1, \nu_2) := \left\{(z_1, z_2) : (u^n, \nu_1(z_1), \nu_2(z_2)) \in A_\delta^{(n)}\right\}.$$

Given $E(u^n, \nu_1, \nu_2)$, if $\mathcal{A}(u^n, \nu_1, \nu_2)$ is nonempty, define

$$\big(Z_1(u^n, \nu_1, \nu_2), Z_2(u^n, \nu_1, \nu_2)\big)$$

as a random pair that is uniformly distributed on $\mathcal{A}(u^n, \nu_1, \nu_2)$. Otherwise, set $Z_i(u^n, \nu_1, \nu_2) = 1$ for $i = 1, 2$.

Next, fix $(w_{10}, w_{20}, w_{1d}, w_{2d})$ and let $E(u^n, v_1^n, v_2^n)$ denote the event where $U^n(w_{10}, w_{20}) = u^n$, $V_1^n(w_{1d}, Z_1|u^n) = v_1^n$ and $V_2^n(w_{2d}, Z_2|u^n) = v_2^n$. For every w_{11} and w_{22}, generate the codewords $X_1^n(w_{11}|u^n, v_1^n)$ and $X_2^n(w_{22}|u^n, v_2^n)$ independently according to the distributions

$$\mathbf{P}\left\{X_i^n(w_{ii}|u^n, v_i^n) = x_i^n \middle| E(u^n, v_1^n, v_2^n)\right\} = \prod_{t=1}^{n} P(x_{it}|u_t, v_{it})$$

for $i = 1, 2$. This completes our codebook construction.

We next describe the encoding and decoding operations. Suppose $W_1 = (w_{10}, w_{1d}, w_{11})$ and $W_2 = (w_{20}, w_{2d}, w_{22})$. Encoders 1 and 2 send the pairs (w_{10}, w_{1d}) and (w_{20}, w_{2d}), respectively, to the cooperation facilitator. Thus for $i = 1, 2$, $\varphi_i(w_i) = (w_{i0}, w_{id})$. The cooperation facilitator then transmits

$$\psi_1\big(\varphi_1(w_1), \varphi_2(w_2)\big) = (w_{20}, Z_1)$$
$$\psi_2\big(\varphi_1(w_1), \varphi_2(w_2)\big) = (w_{10}, Z_2),$$

to encoders 1 and 2, respectively.

Using its knowledge of (w_1, w_{20}, Z_1), encoder 1 uses the (U^n, V_1^n)-codebook to transmit $X_1^n(w_{11}|U^n, V_1^n)$. Similarly, using knowledge obtained from the cooperation facilitator, encoder 2 transmits $X_2^n(w_{22}|U^n, V_2^n)$.

The decoder uses joint typicality decoding. Upon receiving Y^n the decoder looks for a unique pair (w_1, w_2) such that

$$\Big(U^n(w_{10}, w_{20}), V_1^n(w_{1d}, Z_1), V_2^n(w_{2d}, Z_2), X_1^n(w_{11}), X_2^n(w_{22}), Y^n\Big) \in A_\epsilon^{(n)}. \tag{5}$$

If such a (w_1, w_2) doesn't exist or exists but is not unique, the decoder declares an error.

IV. ERROR ANALYSIS

In this section, we study the achievability scheme more closely and provide sufficient conditions for (R_1, R_2) such that the probability of error goes to zero. This immediately leads to Theorem 2 which characterizes an achievable rate region for the MAC with transmitter cooperation.

Suppose the message pair (w_1, w_2) is transmitted, where $w_i = (w_{i0}, w_{id}, w_{ii})$. If (w_1, w_2) is the unique pair that satisfies Equation (5) then there is no error. If such a pair does not exist or is not unique, an error occurs. We denote this event by $\mathcal{E}$. Since directly finding an upper bound on $\mathbf{P}(\mathcal{E})$ is not straightforward, we upper bound $\mathcal{E}$ by the union of a finite number of events and then apply the union bound. We give detailed proofs of the bounds mentioned in this section in Appendix E.

In what follows, we denote $U^n(w_{10}, w_{20})$ and $V_i^n(w_{id}, .|U^n)$ by U^n and $V_i^n(.)$, respectively. In addition, we define

$$X_i^n(.) = X_i^n\big(w_{ii}|U^n, V_i^n(.)\big).$$

We denote instances of $V_i^n(.)$ and $X_i^n(.)$ with $\nu_i(.)$ and $\chi_i(.)$, respectively. We also write V_i^n and X_i^n instead of $V_i^n(w_{id}, Z_i|U^n)$ and $X_i^n(w_{ii}|U^n, V_i^n)$.

We denote the output of the decoder with $(\hat{w}_1, \hat{w}_2)$. We denote $U^n(\hat{w}_{10}, \hat{w}_{20})$ with $\hat{U}^n$ and similarly define $\hat{V}_i^n$ and $\hat{X}_i^n$ for $i = 1, 2$.

We next describe the error events. First, define $\mathcal{E}_0$ as

$$\mathcal{E}_0 = \left\{(U^n, V_1^n, V_2^n) \notin A_\delta^{(n)}\right\}. \tag{6}$$

When $\mathcal{E}_0$ does not occur, the CF transmits (w_{20}, Z_1) and (w_{10}, Z_2) to encoders 1 and 2, respectively, which correspond to a jointly typical triple (U^n, V_1^n, V_2^n). Using the Mutual Covering Lemma for weakly typical sets (Appendix F), we show that $\mathbf{P}(\mathcal{E}_0)$ goes to zero if $\zeta > 4\epsilon$, where ζ is defined by Equation (3).

Next, define $\mathcal{E}_1$ as

$$\mathcal{E}_1 = \left\{(U^n, V_1^n, V_2^n, X_1^n, X_2^n, Y^n) \notin A_\epsilon^{(n)}\right\}.$$

This is the event where the codewords of the transmitted message pair are not jointly typical with the received output Y^n. Then we have $\mathbf{P}(\mathcal{E}_1 \backslash \mathcal{E}_0) \to 0$ as $n \to \infty$ if $\zeta < \Theta(\epsilon) - 4\delta$.

If an error occurs and $\mathcal{E}_1^c$ holds, there must exist a message pair $(\hat{w}_1, \hat{w}_2)$ different from (w_1, w_2) that satisfies (5). The message pair $(\hat{w}_1, \hat{w}_2)$, where $\hat{w}_i = (\hat{w}_{i0}, \hat{w}_{id}, \hat{w}_{ii})$, may have $(\hat{w}_{10}, \hat{w}_{20}) \neq (w_{10}, w_{20})$ or $(\hat{w}_{10}, \hat{w}_{20}) = (w_{10}, w_{20})$.

Define $\mathcal{E}_U$ as the event where $(\hat{w}_{10}, \hat{w}_{20}) \neq (w_{10}, w_{20})$. In this case, $(\hat{U}^n, \hat{V}_1^n, \hat{V}_2^n, \hat{X}_1^n, \hat{X}_2^n)$ and Y^n are independent, which implies that $\mathbf{P}(\mathcal{E}_U)$ goes to zero if $R_1 + R_2 < I(X_1, X_2; Y) - \zeta - 7\epsilon$.

If $(\hat{w}_{10}, \hat{w}_{20}) = (w_{10}, w_{20})$, then either $(\hat{w}_{1d}, \hat{w}_{2d}) \neq (w_{1d}, w_{2d})$ or $(\hat{w}_{1d}, \hat{w}_{2d}) = (w_{1d}, w_{2d})$. If $(\hat{w}_{1d}, \hat{w}_{2d}) \neq (w_{1d}, w_{2d})$, then $\hat{w}_{1d} \neq w_{1d}$ but $\hat{w}_{2d} = w_{2d}$, or $\hat{w}_{2d} \neq w_{2d}$ but $\hat{w}_{1d} = w_{1d}$, or $\hat{w}_{1d} \neq w_{1d}$ *and* $\hat{w}_{2d} \neq w_{2d}$.

Let $(i, j) \in \{(1, 2), (2, 1)\}$. If $\hat{w}_{id} \neq w_{id}$ and $\hat{w}_{jd} = w_{jd}$, we may have $\hat{w}_{jj} \neq w_{jj}$ or $\hat{w}_{jj} = w_{jj}$. We denote the former event by $\mathcal{E}_{V_i X_j}$ and the latter by $\mathcal{E}_{V_i}$. Finally, we denote the event where $\hat{w}_{1d} \neq w_{1d}$ and $\hat{w}_{2d} \neq w_{2d}$ with $\mathcal{E}_{V_1 V_2}$.

For $(i,j) \in \{(1,2),(2,1)\}$, when $\mathcal{E}_{V_i X_j}$ occurs, $(\hat{V}_1^n, \hat{V}_2^n, \hat{X}_1^n, \hat{X}_2^n)$ and Y^n are independent given $(U^n, V_j^n(.))$. This implies $\mathbf{P}(\mathcal{E}_{V_i X_j}) \to 0$ if $(R_i - R_{i0}) + R_{jj} < I(X_1, X_2; Y|U, V_j) - \zeta - 8\epsilon$.

For $(i,j) \in \{(1,2),(2,1)\}$, when $\mathcal{E}_{V_i}$ occurs, we show that $(\hat{V}_1^n, \hat{V}_2^n, \hat{X}_1^n, \hat{X}_2^n)$ and Y^n are independent given $(U^n, V_j^n(.), X_j^n(.))$. This implies $\mathbf{P}(\mathcal{E}_{V_i}) \to 0$ if $R_i - R_{i0} < I(X_i; Y|U, V_j, X_j) - \zeta - 8\epsilon$.

If $\mathcal{E}_{V_1 V_2}$ occurs, $(\hat{V}_1^n, \hat{V}_2^n, \hat{X}_1^n, \hat{X}_2^n)$ and Y^n are independent given U^n. Thus $\mathbf{P}(\mathcal{E}_{V_1 V_2})$ goes to zero if

$$(R_1 - R_{10}) + (R_2 - R_{20}) < I(X_1, X_2; Y|U) - \zeta - 8\epsilon.$$

Finally, if an error occurs and the message pairs have the same (w_{10}, w_{20}) and the same (w_{1d}, w_{2d}), they must have different (w_{11}, w_{22}). We define the events $\mathcal{E}_{X_i}$ and $\mathcal{E}_{X_1 X_2}$ similarly to the events for (w_{1d}, w_{2d}). The relations

$$\hat{X}_i^n \to (U^n, V_1^n, V_2^n, X_j^n) \to Y^n$$
$$(\hat{X}_1^n, \hat{X}_2^n) \to (U^n, V_1^n, V_2^n) \to Y^n,$$

hold for the events $\mathcal{E}_{X_i}$ and $\mathcal{E}_{X_1 X_2}$, respectively. From these relations it follows that

$$\mathbf{P}(\mathcal{E}_{X_i}) \to 0 \text{ if } R_{ii} < I(X_i; Y|U, V_1, V_2, X_j) - 4\epsilon$$
$$\mathbf{P}(\mathcal{E}_{X_1 X_2}) \to 0 \text{ if } R_{11} + R_{22} < I(X_1, X_2; Y|U, V_1, V_2) - 4\epsilon.$$

Not surprisingly, these bounds closely resemble the bounds that appear in the capacity region of the classical MAC.

The bounds given in this section can be simplified further by replacing $R_i - R_{i0}$ and R_{ii} with $(R_i - C_{i0})^+$ and $(R_i - C_i^{\text{in}})^+$, respectively, and noting that the set of all (x,y) that satisfy $(x-a)^+ + (y-b)^+ < c$ is the same as the set of all (x,y) that satisfy $x - a < c$, $y - b < c$, and $(x-a)+(y-b) < c$.

Note that the general error event $\mathcal{E}$ is a subset of the union of the error events defined above. Thus if we apply the union bound and choose δ, ϵ, and ζ to be arbitrarily small, we obtain Theorem 2.

V. THE GAUSSIAN MAC

The Gaussian MAC [15], [16] is defined as the channel $Y_t = X_{1t} + X_{2t} + Z_t$, where $\{Z_t\}_{t=1}^n$ is an i.i.d. Gaussian process independent of (X_1^n, X_2^n) and each Z_t is a Gaussian random variable with mean zero and variance N. In addition, the output power of encoder i is constrained by P_i, that is, $\sum_{t=1}^n x_{it}^2 \leq nP_i$, where x_{it} is the output of encoder i at time t for $i = 1, 2$.

For the Gaussian MAC, we modify the definition of an achievable rate pair by adding the encoder power constraints to the definition of the (n, M_1, M_2) code for a MAC with a CF. Then the rate region $\mathscr{R}_{\text{mod}}$ is achievable for the Gaussian MAC, where $\mathscr{R}_{\text{mod}}$ is the same as $\mathscr{R}$ (Theorem 2) with the additional constraints $\mathbb{E}\big[X_i^2\big] \leq P_i$ for $i = 1, 2$ on the input distribution $P(u, v_1, v_2)P(x_1|u, v_1)P(x_2|u, v_2)$. This follows by replacing entropies with differential entropies and including the input power constraints in the definition of $A_\epsilon^{(n)}$. This is possible since we use weakly typical sets [5, p. 521] (rather than strongly typical sets) in the proof of Theorem 2.



Figure 3. The plot of the maximum sum-rate gain by achieved by our scheme for the Gaussian MAC with $\gamma_1 = \gamma_2 = 10^3$ and $C_1^{\text{in}} = C_2^{\text{in}} = 0.2$ as a function of C_{out}.

If, in the calculation of $\mathscr{R}_{\text{mod}}$, we limit ourselves only to Gaussian input distributions, we get a rate region which we denote by $\mathscr{R}_{\text{G}}$. Note that $\mathscr{R}_{\text{G}}$ is an inner bound for the capacity region of a Gaussian MAC with a CF. We denote the signal to noise ratio of encoder i with $\gamma_i = \frac{P_i}{N}$ and define $\bar{\gamma} = \sqrt{\gamma_1 \gamma_2}$. The rate region $\mathscr{R}_{\text{G}}$ is given by the next theorem.

Theorem 4. *For the Gaussian MAC with a* $(\mathbf{C}_{\text{in}}, \mathbf{C}_{\text{out}})$ *CF, the achievable rate region* $\mathscr{R}_{\text{G}}$ *is given by the set of all rate pairs* (R_1, R_2) *that for* $\{i, j\} = \{1, 2\}$ *satisfy*

$$\begin{aligned}
R_i &< \frac{1}{2}\log(1 + \rho_{ii}^2 \gamma_i) + C_i^{\text{in}} \\
R_i &< \frac{1}{2}\log(1 + \tilde{\rho}_{ii}^2 \gamma_i) + C_{i0} \\
R_1 + R_2 &< \frac{1}{2}\log(1 + \rho_{11}^2 \gamma_1 + \rho_{22}^2 \gamma_2) + C_1^{\text{in}} + C_2^{\text{in}} \\
R_1 + R_2 &< \frac{1}{2}\log(1 + \rho_{ii}^2 \gamma_i + \tilde{\rho}_{jj}^2 \gamma_j) + C_i^{\text{in}} + C_{j0} \\
R_1 + R_2 &< \frac{1}{2}\log\big(1 + (1 - \rho_{10}^2)\gamma_1 + (1 - \rho_{20}^2)\gamma_2 \\
&\qquad + 2\rho_0 \rho_{1d} \rho_{2d} \bar{\gamma}\big) + C_{10} + C_{20} \\
R_1 + R_2 &< \frac{1}{2}\log\big(1 + \gamma_1 + \gamma_2 + 2(\rho_{10}\rho_{20} + \rho_0 \rho_{1d} \rho_{2d})\bar{\gamma}\big)
\end{aligned}$$

for some $\rho_{10}, \rho_{20}, \rho_{1d}, \rho_{2d} \in [0, 1]$*, and nonnegative constants* C_{10} *and* C_{20} *that satisfy Equation (1). In the above inequalities* ρ_0*,* ρ_{ii}*, and* $\tilde{\rho}_{ii}$ *(for* $i = 1, 2$*) are given by*

$$\begin{aligned}
\frac{1}{2}\log\frac{1}{1 - \rho_0^2} &\leq (C_1^{\text{out}} - C_{20}) + (C_2^{\text{out}} - C_{10}) \\
\rho_{ii}^2 &= 1 - \rho_{i0}^2 - \rho_{id}^2 \qquad\qquad (7) \\
\tilde{\rho}_{ii}^2 &= 1 - \rho_{i0}^2 - \rho_0^2 \rho_{id}^2.
\end{aligned}$$

We prove Theorem 4 in Appendix G using techniques similar to [11], in which the capacity region of the Gaussian MAC with conferencing encoders is given.

Using Theorem 4, we can calculate the maximum sum-rate of our scheme for the Gaussian MAC. We define the "sum-rate gain" of a cooperation scheme as the difference between the maximum sum-rate of that scheme and the maximum sum-rate of the classical MAC scheme. In Figure 3, we plot the sum-rate gain of our scheme as a function of $C_1^{\text{out}} = C_2^{\text{out}} =: C_{\text{out}}$ for $\gamma_1 = \gamma_2 = 10^3$, $C_1^{\text{in}} = C_2^{\text{in}} = 0.2$ and $C_{\text{out}} \in [0, 0.25]$. We also plot the conferencing bounds in addition to the no conferencing sum-rate, which is the sum-rate corresponding to a scheme that splits the rate between the coordination and the classical MAC strategies and does not make use of conferencing ($C_{10} = C_{20} = 0$).

Note that for any value of C_{out} for which the gain in sum-rate is greater than $4C_{\text{out}}$, adding a $(C_{\text{in}}, C_{\text{out}})$-CF to the Gaussian MAC results in a network that does not satisfy the edge removal property. The reason is that if we remove the output edges of the $(C_{\text{in}}, C_{\text{out}})$-CF, the decrease in sum-capacity is greater than $4C_{\text{out}}$, which implies the decrease in either R_1 or R_2 (or both) is greater than $2C_{\text{out}}$, which is the total capacity of the removed edges. On the plot, these are the points on our curve which fall above the "edge removal line", that is, the line whose equation is given by $\text{gain} = 4C_{\text{out}}$.

As we see, the scheme that makes no use of conferencing performs well when $C_{\text{out}} \ll C_{\text{in}}$, and the conferencing scheme works well when C_{out} is close to C_{in} (and is optimal when $C_{\text{out}} \geq C_{\text{in}}$). Thus both strategies are necessary for our scheme to perform well over the entire range of C_{out}. In this case study, the maximum sum-rate of $\mathscr{R}_{\text{G}}$ could have been obtained by a carefully designed time sharing between encoders which only cooperate through conferencing and encoders that use our scheme without conferencing. Whether this is representative of our scheme in general (specifically of $\mathscr{R}_{\text{mod}}$ and $\mathscr{R}$) is subject to future research.

VI. CONCLUSION

We study the cost and benefit of cooperation under a general model introduced in this paper. By adapting the coding strategy of Marton [6] for the broadcast channel to the setting of the MAC with cooperating encoders, we suggest a cooperation scheme that combines the ideas of [6] and [7] with the conferencing strategy of Willems [4]. Based on this scheme, we present an inner bound for the MAC with a CF, which is sufficient to show a large gain in sum-capacity as a result of transmitter cooperation.

Throughout the proof of our inner bound, we only make use of weakly typical sets [5, p. 521] rather than strongly typical sets [18, p. 30]. This allows the proof of our achievability result to go through for the Gaussian MAC without the use of quantization. In particular, we present a proof (Appendix F) of the Mutual Covering Lemma [18, p. 208] for weakly typical sets.

ACKNOWLEDGEMENTS

This material is based upon work supported by the National Science Foundation under Grant No. CCF-1321129. The first author thanks Ming Fai Wong, Wei Mao, and Siddharth Jain for useful discussions.

APPENDIX A
THE CONFERENCING ENCODERS MODEL

In the conferencing encoders model, introduced by Willems [4], each encoder sends partial information regarding its message to the other encoder via a noiseless link. The capacity of the links going from encoder 1 to encoder 2 and back are denoted by C_{12} and C_{21}, respectively. At every time step, each encoder sends information to the other encoder that is a function of its own message and what it received from that encoder during the previous time steps. After this "conference" is over, each encoder transmits a codeword over the channel that is a function of its message and information it received during the conference. For a blocklength n code, the amount of information going from encoder 1 to encoder 2 and going back is bounded by nC_{12} and nC_{21} bits, respectively.

Even though the conference can go on for any finite number of steps, the achievability and converse results of Willems [4] demonstrate that a single step of conferencing suffices to achieve capacity. In one-step conferencing, encoder 1 sends a rate C_{12} function of its message to encoder 2 and encoder 2 sends a rate C_{21} function of its message to encoder 1. Then the encoders treat the shared messages as a single rate $C_{12} + C_{21}$ common message and use the channel coding strategy of Slepian and Wolf [17].

We denote the capacity of a MAC $(\mathcal{X}_1 \times \mathcal{X}_2, P(y|x_1, x_2), \mathcal{Y})$ with a (C_{12}, C_{21}) conference with $\mathscr{C}_{\text{conf}}(C_{12}, C_{21})$, which is given by the set of all rate pairs (R_1, R_2) that satisfy

$$\begin{aligned} R_1 &\leq I(X_1; Y|X_2, U) + C_{12} \\ R_2 &\leq I(X_2; Y|X_1, U) + C_{21} \\ R_1 + R_2 &\leq I(X_1, X_2; Y|U) + C_{12} + C_{21} \\ R_1 + R_2 &\leq I(X_1, X_2; Y) \end{aligned} \tag{8}$$

for some distribution $P(u)P(x_1|u)P(x_2|u)$.

Note that the achievable rate region $\mathscr{R}(\mathbf{C}^{\text{in}}, \mathbf{C}^{\text{out}})$ introduced in Section II satisfies the conferencing bounds. For the inner bound, if we choose $|\mathcal{V}_1| = |\mathcal{V}_2| = 1$, and

$$\begin{aligned} C_{10} &= \min\left\{C_1^{\text{in}}, C_2^{\text{out}}\right\} \\ C_{20} &= \min\left\{C_2^{\text{in}}, C_1^{\text{out}}\right\}, \end{aligned}$$

we see that the bounds in the definition of $\mathscr{R}$ simplify to those given by (8) for $C_{12} = C_{10}$ and $C_{21} = C_{20}$. For the outer bound, notice that the inequalities

$$\begin{aligned} R_1 &< I(X_1; Y|U, V_1, V_2, X_2) + C_1^{\text{in}} \\ R_2 &< I(X_2; Y|U, V_1, V_2, X_1) + C_2^{\text{in}} \\ R_1 + R_2 &< I(X_1, X_2; Y|U, V_1, V_2) + C_1^{\text{in}} + C_2^{\text{in}} \\ R_1 + R_2 &< I(X_1, X_2; Y), \end{aligned}$$

which appear in the definition of $\mathscr{R}$ are the same as those in (8) for $C_{12} = C_1^{\text{in}}$ and $C_{21} = C_2^{\text{in}}$, since X_1 and X_2 are independent given (U, V_1, V_2).

APPENDIX B
PROOF OF THEOREM 1

Fix $\mathbf{C}_{\text{in}} = (C_1^{\text{in}}, C_2^{\text{in}})$ for some positive C_1^{in} and C_2^{in} and let $\mathbf{C}_{\text{out}} = (C_{\text{out}}, C_{\text{out}})$. Define $g : \mathbb{R}_{\geq 0} \to \mathbb{R}_{\geq 0}$ as

$$g(C_{\text{out}}) = C_{\text{sum}}(\mathbf{C}_{\text{in}}, \mathbf{C}_{\text{out}}).$$

Then by Theorem 2, $g(C_{\text{out}})$, is bounded from below by the maximum of

$$\begin{aligned}\min\big\{&I(X_1,X_2;Y|U,V_1,V_2)+C_1^{\text{in}}+C_2^{\text{in}},\\ &I(X_1,X_2;Y|U,V_1)+C_1^{\text{in}}+C_{20},\\ &I(X_1,X_2;Y|U,V_2)+C_{10}+C_2^{\text{in}},\\ &I(X_1;Y|U,V_2,X_2)+I(X_2;Y|U,V_1,X_1)+C_{10}+C_{20},\\ &I(X_1,X_2;Y|U)+C_{10}+C_{20},I(X_1,X_2;Y)\big\}\end{aligned} \tag{9}$$

calculated over all alphabets $(\mathcal{U},\mathcal{V}_1,\mathcal{V}_2)$, all nonnegative constants (C_{10},C_{20}) satisfying Equation (1), and all probability distributions $P(u,v_1,v_2)P(x_1|u,v_1)P(x_2|u,v_2)$ that satisfy

$$I(V_1;V_2|U)\le 2C_{\text{out}}-C_{10}-C_{20}.$$

We next find a simpler lower bound for $g(C_{\text{out}})$ by evaluating the minimum in Equation (9) for fixed alphabets, constants, and a special family of distributions. To this end, choose the sets $\mathcal{U}$, $\mathcal{V}_1$, and $\mathcal{V}_2$ such that $|\mathcal{U}|=1$ and $\mathcal{X}_i\subseteq\mathcal{V}_i$ for $i=1,2$. In addition, let $C_{10}=C_{20}=0$ and let $P_a(x_1)P_a(x_2)$ and $P_b(x_1,x_2)$ be distributions such that

$$\begin{aligned}I_a(X_1,X_2;Y)&=\max_{P(x_1)P(x_2)}I(X_1,X_2;Y)\\ I_b(X_1,X_2;Y)&>I_a(X_1,X_2;Y).\end{aligned}$$

Fix $(v_1^*,v_2^*)\in\mathcal{V}_1\times\mathcal{V}_2$. For every $\lambda\in[0,1]$, define

$$\begin{aligned}&P_\lambda(v_1,v_2,x_1,x_2)\\ &\quad=(1-\lambda)\mathbf{1}\{v_1=v_1^*\}\mathbf{1}\{v_2=v_2^*\}P_a(x_1)P_a(x_2)\\ &\qquad+\lambda P_b(v_1,v_2)\mathbf{1}\{x_1=v_1\}\mathbf{1}\{x_2=v_2\}.\end{aligned}$$

Fix $\epsilon>0$. Consider the equation

$$I_{\lambda^*}(V_1;V_2)+2\epsilon\lambda^*=2C_{\text{out}}.$$

By Lemma 7 (see end of appendix),

$$\frac{dC_{\text{out}}}{d\lambda^*}\Big|_{\lambda^*=0^+}=\epsilon>0.$$

Thus by the inverse function theorem, there exists a continuous increasing function $\lambda^*=\lambda^*(C_{\text{out}})$ on $[0,\delta_1)$ for some $\delta_1>0$. Thus for $C_{\text{out}}<\delta_1$, $g(C_{\text{out}})$ is bounded from below by

$$\begin{aligned}\min\big\{&I_{\lambda^*}(X_1,X_2;Y|V_1,V_2)+C_1^{\text{in}}+C_2^{\text{in}},\\ &I_{\lambda^*}(X_1,X_2;Y|V_1)+C_1^{\text{in}},I_{\lambda^*}(X_1,X_2;Y|V_2)+C_2^{\text{in}},\\ &I_{\lambda^*}(X_1;Y|V_2,X_2)+I_{\lambda^*}(X_2;Y|V_1,X_1),\\ &I_{\lambda^*}(X_1,X_2;Y)\big\}.\end{aligned}$$

One of the terms that appears in the above lower bound is $I_{\lambda^*}(X_1;Y|V_2,X_2)+I_{\lambda^*}(X_2;Y|V_1,X_1)$. We can further bound this expression using the next lemma.

Lemma 5. *For any memoryless MAC,*

$$I(X_1;Y|X_2)+I(X_2;Y|X_1)\ge I(X_1,X_2;Y)-I(X_1;X_2).$$

Proof: We have

$$\begin{aligned}&I(X_1;Y|X_2)+I(X_2;Y|X_1)+I(X_1;X_2)\\ &\quad=I(X_1;Y|X_2)+I(X_2;X_1,Y)\\ &\quad=I(X_1;Y|X_2)+I(X_2;Y)+I(X_1;X_2|Y)\\ &\quad=I(X_1,X_2;Y)+I(X_1;X_2|Y).\end{aligned}$$

The result of the lemma now follows from the nonnegativity of mutual information. □

If in the above lemma we replace X_i with (V_i,X_i) with arbitrary distribution $P(v_1,v_2)P(x_1|v_1)P(x_2|v_2)$ and simplify we get

$$I(X_1;Y|V_2,X_2)+I(X_2;Y|V_1,X_1)\ge I(X_1,X_2;Y)-I(V_1;V_2),$$

since $(V_1,V_2)\to(X_1,X_2)\to Y$ is a Markov chain and

$$\begin{aligned}&I(V_1,X_1;V_2,X_2)\\ &\quad=H(V_1,X_1)+H(V_2,X_2)-H(V_1,V_2,X_1,X_2)\\ &\quad=I(V_1;V_2).\end{aligned}$$

Therefore, for $C_{\text{out}}<\delta_1$, $g(C_{\text{out}})$ is bounded from below by

$$\min_{i\in\{0,1,2,3\}}g_i(C_{\text{out}}),$$

where

$$\begin{aligned}g_0(C_{\text{out}})&=I_{\lambda^*}(X_1,X_2;Y)-I_{\lambda^*}(V_1;V_2)\\ g_1(C_{\text{out}})&=I_{\lambda^*}(X_1,X_2;Y|V_1)+C_1^{\text{in}}\\ g_2(C_{\text{out}})&=I_{\lambda^*}(X_1,X_2;Y|V_2)+C_2^{\text{in}}\\ g_3(C_{\text{out}})&=I_{\lambda^*}(X_1,X_2;Y|V_1,V_2)+C_1^{\text{in}}+C_2^{\text{in}}.\end{aligned}$$

Note that if $C_{\text{out}}=0$, then $\lambda^*(C_{\text{out}})=0$ and

$$\min_{i\in\{0,1,2,3\}}g_i(C_{\text{out}})=g_0(0)=I_a(X_1,X_2;Y),$$

since

$$P_0(v_1,v_2,x_1,x_2)=\mathbf{1}\{v_1=v_1^*\}\mathbf{1}\{v_2=v_2^*\}P_a(x_1)P_a(x_2)$$

and $\min\{C_1^{\text{in}},C_2^{\text{in}}\}>0$. Furthermore, as the g_i's are continuous in C_{out}, there exists a positive δ smaller than δ_1 such that for every $C_{\text{out}}<\delta$,

$$\min_{i\in\{0,1,2,3\}}g_i(C_{\text{out}})=g_0(C_{\text{out}}).$$

Therefore, for $C_{\text{out}}<\delta$, $g(C_{\text{out}})$ is bounded from below by

$$g_0(C_{\text{out}})=I_{\lambda^*}(X_1,X_2;Y)-I_{\lambda^*}(V_1;V_2).$$

Since, in addition,

$$g(0)=g_0(0)=I_a(X_1,X_2;Y),$$

we have

$$\begin{aligned}g'(0)\ge g_0'(0)&=\frac{dg_0}{dC_{\text{out}}}\Big|_{C_{\text{out}}=0^+}\\ &=\frac{dg_0}{d\lambda^*}\Big|_{\lambda^*=0^+}\cdot\frac{d\lambda^*}{dC_{\text{out}}}\Big|_{C_{\text{out}}=0^+}\\ &\ge\frac{1}{\epsilon}\big(I_b(X_1,X_2;Y)-I_a(X_1,X_2;Y)\big),\end{aligned}$$

where the last inequality follows from Lemma 7 (see end of appendix). Since ϵ can be chosen to be arbitrarily small, we must have $g'(0)=+\infty$.

In the special case where our channel is a Gaussian MAC, if we choose $\rho_{10}=\rho_{20}=0$, $\rho_{1d}=\rho_{2d}=:\rho_d$, and $C_{10}=C_{20}=0$ in Theorem 4, we see that $g(C_{\text{out}})$ is bounded from below by the maximum of

$$\min_{0\le i\le 4}f_i(\rho_0,\rho_d),$$

calculated over (ρ_0, ρ_d), where $\rho_d \in [0,1]$,

$$0 \leq \rho_0 \leq \sqrt{1 - e^{-4C_{\text{out}}}} =: \rho_0(C_{\text{out}}).$$

The f_i's are defined as

$$\begin{aligned}
f_0(\rho_0, \rho_d) &= \frac{1}{2}\log(1 + \gamma_1 + \gamma_2 + 2\rho_0\rho_d^2\sqrt{\gamma_1\gamma_2}) \\
f_1(\rho_0, \rho_d) &= \frac{1}{2}\log\big(1 + (1 - \rho_0^2\rho_d^2)\gamma_1\big) \\
&\quad + \frac{1}{2}\log\big(1 + (1 - \rho_0^2\rho_d^2)\gamma_2\big) \\
f_2(\rho_0, \rho_d) &= \frac{1}{2}\log\big(1 + (1 - \rho_d^2)\gamma_1 + (1 - \rho_0^2\rho_d^2)\gamma_2\big) + C_1^{\text{in}} \\
f_3(\rho_0, \rho_d) &= \frac{1}{2}\log\big(1 + (1 - \rho_0^2\rho_d^2)\gamma_1 + (1 - \rho_d^2)\gamma_2\big) + C_2^{\text{in}} \\
f_4(\rho_0, \rho_d) &= \frac{1}{2}\log\big(1 + (1 - \rho_d^2)\gamma_1 + (1 - \rho_d^2)\gamma_2\big) + C_1^{\text{in}} + C_2^{\text{in}}.
\end{aligned}$$

Next define the function $F(\rho_0, \rho_d^*)$ as

$$F(\rho_0, \rho_d) = f_0(\rho_0, \rho_d) - \min_{1 \leq i \leq 4} f_i(\rho_0, \rho_d).$$

Note that $F(1,0) < 0$ since γ_1, γ_2, C_1^{in}, and C_2^{in} are positive. Since F is continuous, there exists $\rho_d^* > 0$ such that $F(1, \rho_d^*) < 0$. However, for any ρ_d, $F(., \rho_d)$ is an increasing function of ρ_0. Thus for any $\rho_0 \leq \rho_0(C_{\text{out}})$,

$$F(\rho_0, \rho_d^*) \leq F(1, \rho_d^*) < 0.$$

In particular, $F\big(\rho_0(C_{\text{out}}), \rho\big) < 0$. This implies

$$g(C_{\text{out}}) > f_0\big(\rho_0(C_{\text{out}}), \rho_d^*\big).$$

To calculate $f_0\big(\rho_0(C_{\text{out}}), \rho_d^*\big)$ we make use of the next lemma.

Lemma 6. *For constants a and b ($b > 0$) we have*

$$\log\big(1 + a\sqrt{1 - e^{-bx}}\big) = a\sqrt{bx} + o(\sqrt{x}) \textit{ for } x > 0.$$

Proof: We have

$$\begin{aligned}
\log\big(1 + a\sqrt{1 - e^{-bx}}\big) &= \log\big(1 + a\sqrt{bx + o(x)}\big) \\
&= \log\big(1 + a\sqrt{bx} + o(\sqrt{x})\big) \\
&= a\sqrt{bx} + o(\sqrt{x}).
\end{aligned}$$

□

By the previous lemma,

$$\begin{aligned}
f_0\big(\rho_0(C_{\text{out}}), \rho_d^*\big) - g(0) &= \frac{1}{2}\log\big(1 + \frac{a}{2}\sqrt{1 - e^{-4C_{\text{out}}}}\big) \\
&= a\sqrt{C_{\text{out}}} + o\big(\sqrt{C_{\text{out}}}\big),
\end{aligned}$$

where $g(0) = \frac{1}{2}\log(1 + \gamma_1 + \gamma_2)$ and

$$a = \frac{4\rho_d^{*2}\sqrt{\gamma_1\gamma_2}}{1 + \gamma_1 + \gamma_2}.$$

To get the result stated in the theorem, it suffices to choose α such that $0 < \alpha < a$. The next lemma, used in the appendix to calculate the derivatives of $I_\lambda(V_1; V_2)$ and $I_\lambda(X_1, X_2; Y)$, follows.

Lemma 7. *Let $P_0(x_1)P_0(x_2)$ and $P_1(x_1, x_2)$ be joint distributions on $\mathcal{X}_1 \times \mathcal{X}_2$. For every $\lambda \in [0,1]$, define the distribution $P_\lambda(x_1, x_2)$ as*

$$P_\lambda(x_1, x_2) = \lambda P_1(x_1, x_2) + (1 - \lambda)P_0(x_1)P_0(x_2).$$

Then

$$\frac{d}{d\lambda}I_\lambda(X_1; X_2)\Big|_{\lambda = 0^+} = 0.$$

Furthermore, if $P_\lambda(x_1, x_2, y) = P_\lambda(x_1, x_2)P(y|x_1, x_2)$, then

$$\frac{d}{d\lambda}I_\lambda(X_1, X_2; Y)\Big|_{\lambda = 0^+} \geq I_1(X_1, X_2; Y) - I_0(X_1, X_2; Y).$$

Proof: Note that for every (x_1, x_2),

$$\frac{d}{d\lambda}P_\lambda(x_1, x_2) = P_1(x_1, x_2) - P_0(x_1)P(x_2).$$

Since

$$I_\lambda(X_1; X_2) = \sum_{x_1, x_2} P_\lambda(x_1, x_2)\log\frac{P_\lambda(x_1, x_2)}{P_\lambda(x_1)P_\lambda(x_2)},$$

we have

$$\begin{aligned}
&\frac{d}{d\lambda}I_\lambda(X_1; X_2) \\
&\quad = \sum_{x_1, x_2}\big(P_1(x_1, x_2) - P_0(x_1)P_0(x_2)\big)\log\frac{P_\lambda(x_1, x_2)}{P_\lambda(x_1)P_\lambda(x_2)} \\
&\qquad + \sum_{x_1, x_2} P_\lambda(x_1, x_2)\Bigg(\frac{P_1(x_1, x_2) - P_0(x_1)P_0(x_2)}{P_\lambda(x_1, x_2)} \\
&\qquad\qquad - \frac{P_1(x_1) - P_0(x_1)}{P_\lambda(x_1)} - \frac{P_1(x_2) - P_0(x_2)}{P_\lambda(x_2)}\Bigg) \\
&\quad = \sum_{x_1, x_2}\big(P_1(x_1, x_2) - P_0(x_1)P_0(x_2)\big)\log\frac{P_\lambda(x_1, x_2)}{P_\lambda(x_1)P_\lambda(x_2)}.
\end{aligned}$$

Thus

$$\frac{d}{d\lambda}I_\lambda(X_1; X_2)\Big|_{\lambda = 0^+} = 0.$$

For the second part, we write

$$I_\lambda(X_1, X_2; Y) = H_\lambda(Y) - H_\lambda(Y|X_1, X_2)$$

and calculate the derivatives of $H_\lambda(Y)$ and $H_\lambda(Y|X_1, X_2)$ separately. Note that

$$H_\lambda(Y) = -\sum_y P_\lambda(y)\log P_\lambda(y),$$

thus

$$\begin{aligned}
\frac{dH_\lambda(Y)}{d\lambda} &= -\sum_y\big(1 + \log P_\lambda(y)\big)\big(P_1(y) - P_0(y)\big) \\
&= \sum_y\big(P_0(y) - P_1(y)\big)\log P_\lambda(y) \\
&= H_0(Y) + H_1(Y) \\
&\quad + D\big(P_1(y)\|P_\lambda(y)\big) - D\big(P_0(y)\|P_\lambda(y)\big).
\end{aligned}$$

Furthermore, we have

$$H(Y|X_1, X_2) = \sum_{x_1, x_2} P_\lambda(x_1, x_2)H(Y|X_1 = x_1, X_2 = x_2),$$

so

$$\frac{d}{d\lambda}H_\lambda(Y|X_1, X_2) = H_1(Y|X_1, X_2) - H_0(Y|X_1, X_2).$$

Therefore,

$$\frac{d}{d\lambda} I_\lambda(X_1, X_2; Y) = I_1(X_1, X_2; Y) - I_0(X_1, X_2; Y) \\ + D\big(P_1(y) \| P_\lambda(y)\big) - D\big(P_0(y) \| P_\lambda(y)\big).$$

Thus

$$\frac{d}{d\lambda} I_\lambda(X_1, X_2; Y)\Big|_{\lambda = 0^+} \geq I_1(X_1, X_2; Y) - I_0(X_1, X_2; Y).$$

$\square$

APPENDIX C
THE $C_1^{\text{in}} = C_2^{\text{in}} = \infty$ CASE

In this appendix, we find a simple representation for $\mathscr{R}(\mathbf{C}_{\text{in}}, \mathbf{C}_{\text{out}})$ (Section II) in the case where $C_1^{\text{in}} = C_2^{\text{in}} = \infty$. If we denote this region with $\mathscr{R}$, then $\mathscr{R}$ consists of all rate pairs (R_1, R_2) that satisfy

$$\begin{aligned} R_1 &< I(X_1; Y | U, V_2, X_2) + C_{10} \\ R_2 &< I(X_2; Y | U, V_1, X_1) + C_{20} \\ R_1 + R_2 &< I(X_1, X_2; Y | U) + C_{10} + C_{20} \\ R_1 + R_2 &< I(X_1, X_2; Y), \end{aligned}$$

for some $C_{10} \leq C_2^{\text{out}}$ and $C_{20} \leq C_1^{\text{out}}$, and some distribution $P(u, v_1, v_2) P(x_1 | u, v_1) P(x_2 | u, v_2)$ that satisfies

$$I(V_1; V_2 | U) \leq (C_1^{\text{out}} - C_{20}) + (C_2^{\text{out}} - C_{10}) \tag{10}$$

Note that this region is contained in the region consisting of all rate pairs (R_1, R_2) that satisfy

$$\begin{aligned} R_1 &< I(X_1; Y | U, X_2) + C_{10} \\ R_2 &< I(X_2; Y | U, X_1) + C_{20} \\ R_1 + R_2 &< I(X_1, X_2; Y | U) + C_{10} + C_{20} \\ R_1 + R_2 &< I(X_1, X_2; Y), \end{aligned}$$

for some $C_{10} \leq C_2^{\text{out}}$ and $C_{20} \leq C_1^{\text{out}}$, and some distribution $P(u, x_1, x_2)$ that satisfies

$$I(X_1; X_2 | U) \leq (C_1^{\text{out}} - C_{20}) + (C_2^{\text{out}} - C_{10}). \tag{11}$$

This follows from the fact that

$$(U, V_1, V_2) \to (X_1, X_2) \to Y$$

is a Markov chain, and any distribution $P(u, v_1, v_2) P(x_1 | u, v_1) P(x_2 | u, v_2)$ that satisfies Equation (10) also satisfies Equation (11), since

$$I(X_1; X_2 | U) \leq I(V_1, X_1; V_2, X_2 | U) = I(V_1; V_2 | U).$$

To show that these two regions are in fact equal, it now suffices to choose $\mathcal{V}_i = \mathcal{X}_i$ for $i = 1, 2$, and

$$\begin{aligned} &P(u, v_1, v_2) P(x_1 | u, v_1) P(x_2 | u, v_2) \\ &\qquad = P(u, v_1, v_2) \delta(x_1 - v_1) \delta(x_2 - v_2) \end{aligned}$$

in the definition of the first region.

APPENDIX D
PROOF OF THEOREM 3

Fix $\lambda \in (0, 1)$. Suppose $(R_{1a}, R_{2a}) \in \mathscr{R}_a$ and $(R_{1b}, R_{2b}) \in \mathscr{R}_b$. Then there exist constants (C_{10}^a, C_{20}^a) and (C_{10}^b, C_{20}^b) and input distributions

$$\begin{aligned} &P_a(u) P_a(v_1, v_2 | u) P_a(x_1 | u, v_1) P_a(x_2 | u, v_2) \\ &P_b(u) P_b(v_1, v_2 | u) P_b(x_1 | u, v_1) P_b(x_2 | u, v_2) \end{aligned}$$

that satisfy the constraints of $\mathscr{R}_a$ and $\mathscr{R}_b$ for the rate pairs (R_{1a}, R_{2a}) and (R_{1b}, R_{2b}), respectively. We show that the rate pair $(R_{1\lambda}, R_{2\lambda}) \in \mathscr{R}_\lambda$, where for $i = 1, 2$,

$$R_{i\lambda} = \lambda R_{ia} + (1 - \lambda) R_{ib}.$$

First define

$$C_{i0}^\lambda = \lambda C_{i0}^a + (1 - \lambda) C_{i0}^b$$

for $i = 1, 2$. Notice that by this definition, these constants satisfy the constraints of $\mathscr{R}_\lambda$.

Next, consider the input distribution

$$P(u') P(v_1, v_2 | u') P(x_1 | u', v_1) P(x_2 | u', v_2) \tag{12}$$

where $u' = (u, s)$, $s \in \{a, b\}$, $P(s = a) = \lambda$,

$$P(u | s) = \begin{cases} P_a(u) & \text{if } s = a \\ P_b(u) & \text{if } s = b, \end{cases}$$

and

$$P(v_1, v_2 | u, s) = \begin{cases} P_a(v_1, v_2 | u) & \text{if } s = a \\ P_b(v_1, v_2 | u) & \text{if } s = b. \end{cases}$$

Define $P(x_1 | u', v_1)$ and $P(x_2 | u', v_2)$ similarly. We show that $(R_{1\lambda}, R_{2\lambda})$ satisfies the bounds of $\mathscr{R}_\lambda$ for this input distribution. Note that for any mutual information of the form $I(A; B | U, C)$ we have

$$I(A; B | U', C) = \lambda I_a(A; B | U, C) + (1 - \lambda) I_b(A; B | U, C),$$

where A, B, and C are arbitrary random variables. Except for $I(X_1, X_2; Y)$, all the other mutual information terms appearing in the definition of $\mathscr{R}_\lambda$ are of this form. If we compute $I(X_1, X_2; Y)$ with respect to (12) we get

$$\begin{aligned} I(X_1, X_2; Y) &\geq I(X_1, X_2; Y | S) \\ &= \lambda I_a(X_1, X_2; Y) + (1 - \lambda) I_b(X_1, X_2; Y), \end{aligned}$$

where the inequality holds since

$$S \to (X_1, X_2) \to Y$$

is a Markov chain. Thus $(R_{1\lambda}, R_{2\lambda}) \in \mathscr{R}_\lambda$ and the proof is complete.

APPENDIX E
DETAILS OF ERROR ANALYSIS

Before going into the proofs of the error bounds of Section IV we need to study the the distribution of our code in more detail. Note that

$$\begin{aligned} &P_{\text{code}}(u^n, \nu_1, \nu_2, v_1^n, v_2^n, x_1^n, x_2^n, y^n) \\ &\qquad = P(u^n) P(\nu_1 | u^n) P(\nu_2 | u^n) P(v_1^n, v_2^n | u^n, \nu_1, \nu_2) \\ &\qquad\quad \times P(x_1^n | u^n, v_1^n) P(x_2^n | u^n, v_2^n) P(y^n | x_1^n, x_2^n). \end{aligned}$$

The next lemma relates $P_{\text{code}}(v_1^n, v_2^n|u^n)$ to the marginals of $P(v_1^n, v_2^n|u^n)$, which is the distribution we use in the definition of $A_\delta^{(n)}$ and $A_\epsilon^{(n)}$.

Lemma 8. *For all* (u^n, v_1^n, v_2^n),

$$P_{\text{code}}(v_1^n, v_2^n|u^n) \le 2^{n(C_{1d}+C_{2d})} P(v_1^n|u^n) P(v_2^n|u^n).$$

Proof: Note that

$$\begin{aligned} &P_{\text{code}}(v_1^n, v_2^n|u^n) \\ &\quad = \sum_{\nu_1,\nu_2} P(\nu_1|u^n) P(\nu_2|u^n) P(v_1^n, v_2^n|u^n, \nu_1, \nu_2). \end{aligned} \tag{13}$$

We have

$$P(v_1^n, v_2^n|u^n, \nu_1, \nu_2) \le \mathbf{1}\{\nu_1^{-1}(v_1^n) \ne \emptyset\}\mathbf{1}\{\nu_2^{-1}(v_2^n) \ne \emptyset\},$$

where $\nu_i^{-1}(v_i^n)$, for $i = 1, 2$, is defined as

$$\nu_i^{-1}(v_i^n) = \{z : \nu_i(z) = v_i^n\}.$$

We thus calculate, for $i = 1, 2$,

$$\begin{aligned} &\sum_{\nu_i} P(\nu_i|u^n)\mathbf{1}\{\nu_i^{-1}(v_i^n) \ne \emptyset\} \\ &\quad = 1 - \sum_{\nu_i} P(\nu_i|u^n)\mathbf{1}\{\nu_i^{-1}(v_i^n) = \emptyset\} \\ &\quad = 1 - \big(1 - P(v_i^n|u^n)\big)^{2^{nC_{id}}} \\ &\quad \le 2^{nC_{id}} P(v_i^n|u^n), \end{aligned}$$

where the last inequality follows from the fact that $1 - \alpha x \le (1-x)^\alpha$ for all nonnegative α and x. Therefore,

$$\begin{aligned} P_{\text{code}}(v_1^n, v_2^n|u^n) &\le \sum_{\nu_1} P(\nu_1|u^n)\mathbf{1}\{\nu_1^{-1}(v_1^n) \ne \emptyset\} \\ &\quad \times \sum_{\nu_2} P(\nu_2|u^n)\mathbf{1}\{\nu_2^{-1}(v_2^n) \ne \emptyset\} \\ &\le 2^{n(C_{1d}+C_{2d})} P(v_1^n|u^n) P(v_2^n|u^n), \end{aligned}$$

and the proof is complete. □

Using the next lemma, which relates the value of a joint distribution to the values of its marginals, we bound $P_{\text{code}}(v_1^n, v_2^n|u^n)$ in terms of $P(v_1^n, v_2^n|u^n)$.

Lemma 9. *For every* $(u^n, v_1^n, v_2^n) \in A_\delta^{(n)}$,

$$2^{n(I(V_1;V_2|U)-4\delta)} \le \frac{P(v_1^n, v_2^n|u^n)}{P(v_1^n|u^n)P(v_2^n|u^n)} \le 2^{n(I(V_1;V_2|U)+4\delta)}.$$

Proof: For every $(u^n, v_1^n, v_2^n) \in A_\delta^{(n)}$, we have

$$\begin{aligned} \frac{P(v_1^n, v_2^n|u^n)}{P(v_1^n|u^n)P(v_2^n|u^n)} &= \frac{P(u^n)P(u^n, v_1^n, v_2^n)}{P(u^n, v_1^n)P(u^n, v_2^n)} \\ &\le \frac{2^{-n(H(U)-\delta)}2^{-n(H(U,V_1,V_2)-\delta)}}{2^{-n(H(U,V_1)+\delta)}2^{-n(H(U,V_2)+\delta)}} \\ &= 2^{n(I(V_1;V_2|U)+4\delta)}. \end{aligned}$$

The lower bound is proved similarly. □

Corollary 10. *For all* $(u^n, v_1^n, v_2^n) \in A_\delta^{(n)}$,

$$P_{\text{code}}(v_1^n, v_2^n|u^n) \le 2^{n(\zeta+4\delta)} P(v_1^n, v_2^n|u^n),$$

where $\zeta := C_{1d} + C_{2d} - I(V_1;V_2|U)$.

Next we prove upper bounds on the probabilities of the error events defined in Section IV.

Bound on $\mathbf{P}(\mathcal{E}_0)$: From the definition of $\mathcal{E}_0$ (Equation (6)) it follows

$$\mathbf{P}(\mathcal{E}_0) = 1 - \sum_{A_\delta^{(n)}} P(u^n) P_{\text{code}}(v_1^n, v_2^n|u^n).$$

Let $A_\delta^{(n)}(u^n)$ denote the set of all pairs (v_1^n, v_2^n) such that (u^n, v_1^n, v_2^n) is in $A_\delta^{(n)}$. Then

$$\begin{aligned} &\sum_{A_\delta^{(n)}} P(u^n) P_{\text{code}}(v_1^n, v_2^n|u^n) \\ &\quad = \sum_{A_\delta^{(n)}} P(u^n) \sum_{\nu_1,\nu_2} P(\nu_1|u^n) P(\nu_2|u^n) P(v_1^n, v_2^n|u^n, \nu_1, \nu_2) \\ &\quad = \sum_{A_\delta^{(n)}(U)} P(u^n) \sum_{\nu_1,\nu_2} \Big(P(\nu_1|u^n) P(\nu_2|u^n) \\ &\qquad\qquad \times \sum_{A_\delta^{(n)}(u^n)} P(v_1^n, v_2^n|u^n, \nu_1, \nu_2) \Big). \end{aligned}$$

Note that the innermost sum equals

$$\sum_{A_\delta^{(n)}(u^n)} P(v_1^n, v_2^n|u^n, \nu_1, \nu_2) = \begin{cases} 1 & \text{if } \mathcal{A}(u^n, \nu_1, \nu_2) \ne \emptyset \\ 0 & \text{otherwise.} \end{cases}$$

Thus

$$\begin{aligned} &\sum_{A_\delta^{(n)}} P(u^n) P_{\text{code}}(v_1^n, v_2^n|u^n) \\ &\qquad = \sum_{u^n,\nu_1,\nu_2} P(u^n) P(\nu_1|u^n) P(\nu_2|u^n) \mathbf{1}\{\mathcal{A} \ne \emptyset\}, \end{aligned}$$

which implies

$$\begin{aligned} \mathbf{P}(\mathcal{E}_0) &= \sum_{u^n,\nu_1,\nu_2} P(u^n) P(\nu_1|u^n) P(\nu_2|u^n) \mathbf{1}\{\mathcal{A} = \emptyset\} \\ &= \mathbf{P}\left\{\mathcal{A}(U^n, V_1^n(.), V_2^n(.)) = \emptyset\right\}. \end{aligned}$$

The last term goes to zero if $\zeta > 4\delta$ (by the Mutual Covering Lemma discussed in Appendix F).

Bound on $\mathbf{P}(\mathcal{E}_1 \setminus \mathcal{E}_0)$: Define the set $B^{(n)}$ as the set of all $(u^n, v_1^n, v_2^n, x_1^n, x_2^n, y^n)$ where $(u^n, v_1^n, v_2^n) \in A_\delta^{(n)}$ but

$$(u^n, v_1^n, v_2^n, x_1^n, x_2^n, y^n) \notin A_\epsilon^{(n)}.$$

Then we have

$$\begin{aligned} \mathbf{P}(\mathcal{E}_1 \setminus \mathcal{E}_0) &= \sum_{B^{(n)}} P(u^n) P_{\text{code}}(v_1^n, v_2^n|u^n) \\ &\qquad \times P(x_1^n|u^n, v_1^n) P(x_2^n|u^n, v_2^n) P(y^n|x_1^n, x_2^n). \end{aligned}$$

Since the sum is only over all typical triples (u^n, v_1^n, v_2^n), Corollary 10 implies

$$
\begin{aligned}
\mathbf{P}(\mathcal{E}_1 \setminus \mathcal{E}_0) &\le 2^{n(\zeta+4\delta)} \\
&\quad \times \sum_{\mathcal{B}^{(n)}} \Big(P(u^n)P(v_1^n, v_2^n|u^n)P(x_1^n|u^n, v_1^n) \\
&\qquad \times P(x_2^n|u^n, v_2^n)P(y^n|x_1^n, x_2^n) \Big) \\
&\le 2^{n(\zeta+4\delta)}\, \mathbf{P}\left\{ (A_\epsilon^{(n)})^c \right\} \\
&\le 2^{n(\zeta+4\delta)} 2^{-n\Theta(\epsilon)}.
\end{aligned}
$$

Thus $\mathbf{P}(\mathcal{E}_1 \setminus \mathcal{E}_0)$ goes to zero if $\zeta < \Theta(\epsilon) - 4\delta$. Since

$$
\mathbf{P}(\mathcal{E}_0 \cup \mathcal{E}_1) = \mathbf{P}(\mathcal{E}_0) + \mathbf{P}(\mathcal{E}_1 \setminus \mathcal{E}_0),
$$

$\mathbf{P}(\mathcal{E}_0 \cup \mathcal{E}_1)$ goes to zero if we choose $\delta > 0$ and $\zeta > 0$ such that $\delta < \frac{1}{8}\Theta(\epsilon)$ and $4\delta < \zeta < \Theta(\epsilon) - 4\delta$.

Bound on $\mathbf{P}(\mathcal{E}_U)$: If $\mathcal{E}_U$ occurs, then

$$
(\hat{U}^n, \hat{V}_1^n, \hat{V}_2^n, \hat{X}_1^n, \hat{X}_2^n, Y^n) \in A_\epsilon^{(n)},
$$

even though $(\hat{U}^n, \hat{V}_1^n, \hat{V}_2^n, \hat{X}_1^n, \hat{X}_2^n)$ is independent of $(U^n, V_1^n, V_2^n, X_1^n, X_2^n)$ (and thus of Y^n) by our code design. Let $A_\epsilon^{(n)}(Y)$ denote the typical set with respect to $P(y)$ and suppose $y^n \in A_\epsilon^{(n)}(Y)$. Then let $A_\epsilon^{(n)}(y^n)$ denote the set of all $(u^n, v_1^n, v_2^n, x_1^n, x_2^n)$ that are jointly typical with y^n. Then by Theorem 15.2.2 of [5], $|A_\epsilon^{(n)}(y^n)| \le 2^{n(H(U,V_1,V_2,X_1,X_2|Y)+2\epsilon)}$. Thus $\mathbf{P}(\mathcal{E}_U)$ is bounded from above by

$$
2^{n(R_1+R_2)} \sum_{A_\epsilon^{(n)}(Y)} P_{\text{code}}(y^n) \sum_{A_\epsilon^{(n)}(y^n)} P_{\text{code}}(u^n, v_1^n, v_2^n, x_1^n, x_2^n).
$$

We now use Corollary 10 to get

$$
\begin{aligned}
&\sum_{A_\epsilon^{(n)}(y^n)} P_{\text{code}}(u^n, v_1^n, v_2^n, x_1^n, x_2^n) \\
&\quad \le 2^{n(\zeta+4\epsilon)} \sum_{A_\epsilon^{(n)}(y^n)} P(u^n, v_1^n, v_2^n, x_1^n, x_2^n) \\
&\quad \le 2^{n(\zeta+4\epsilon)} \times 2^{n(H(U,V_1,V_2,X_1,X_2|Y)+2\epsilon)} \\
&\qquad \times 2^{-n(H(U,V_1,V_2,X_1,X_2)-\epsilon)} \\
&\quad = 2^{-n(I(X_1,X_2;Y)-\zeta-7\epsilon)}.
\end{aligned}
$$

Thus $\mathbf{P}(\mathcal{E}_U) \to 0$ if

$$
R_1 + R_2 < I(X_1, X_2; Y) - \zeta - 7\epsilon.
$$

Bound on $\mathbf{P}(\mathcal{E}_{V_1X_2})$: If $\mathcal{E}_{V_1X_2}$ occurs, then

$$
(\hat{w}_{10}, \hat{w}_{20}, \hat{w}_{2d}) = (w_{10}, w_{20}, w_{2d}),
$$

but $\hat{w}_{1d} \ne w_{1d}$ and $\hat{w}_{22} \ne w_{22}$. This implies that there are at most $2^{n(R_1-C_{10})^+}$ and $2^{n(R_2-C_2^{\text{in}})^+}$ possible values for $\hat{w}_1$ and $\hat{w}_2$, respectively.

In this case

$$
\begin{aligned}
&P(v_1^n, v_2^n, \hat{v}_1^n, \hat{v}_2^n|u^n, \nu_2) \\
&\quad = \sum_{\nu_1, \hat{\nu}_1} \Big(P(\nu_1|u^n)P(\hat{\nu}_1|u^n) \\
&\qquad \times P(v_1^n, v_2^n|u^n, \nu_1, \nu_2)P(\hat{v}_1^n, \hat{v}_2^n|u^n, \hat{\nu}_1, \nu_2) \Big) \\
&\quad = P(v_1^n, v_2^n|u^n, \nu_2)P(\hat{v}_1^n, \hat{v}_2^n|u^n, \nu_2).
\end{aligned}
$$

Thus we have the Markov chain

$$
(\hat{V}_1^n, \hat{V}_2^n, \hat{X}_1^n, \hat{X}_2^n) \to (U^n, V_2^n(.)) \to Y^n.
$$

Therefore we can bound $\mathbf{P}(\mathcal{E}_{V_1})$ from above by

$$
\begin{aligned}
&2^{n((R_1-C_{10})^+ + (R_2-C_2^{\text{in}})^+)} \\
&\quad \times \sum_{A_\epsilon^{(n)}} \sum_{\nu_2} P_{\text{code}}(u^n, \nu_2, y^n)P_{\text{code}}(v_1^n, v_2^n, x_1^n, x_2^n|u^n, \nu_2),
\end{aligned}
$$

We rewrite the sum as

$$
\begin{aligned}
&\sum_{A_\epsilon^{(n)}} \sum_{\nu_2} P_{\text{code}}(u^n, \nu_2, y^n)P_{\text{code}}(v_1^n, v_2^n, x_1^n, x_2^n|u^n, \nu_2) \qquad (14) \\
&\quad = \sum_{A_\epsilon^{(n)}} \Big(P(u^n)P(x_1^n, x_2^n|u^n, v_1^n, v_2^n) \\
&\qquad \times \sum_{\nu_2} P_{\text{code}}(\nu_2, y^n|u^n)P_{\text{code}}(v_1^n, v_2^n|u^n, \nu_2) \Big).
\end{aligned}
$$

Next, we provide an upper bound for the inner sum.

$$
\begin{aligned}
&\sum_{\nu_2} P_{\text{code}}(\nu_2, y^n|u^n)P_{\text{code}}(v_1^n, v_2^n|u^n, \nu_2) \qquad (15) \\
&\quad \le \sum_{\nu_1, \nu_2} P(\nu_1|u^n)P_{\text{code}}(\nu_2, y^n|u^n)P_{\text{code}}(v_1^n, v_2^n|u^n, \nu_1, \nu_2) \\
&\quad \le \sum_{\nu_1, \nu_2} \Big(P(\nu_1|u^n)P_{\text{code}}(\nu_2, y^n|u^n) \\
&\qquad \times \mathbf{1}\{\nu_1^{-1}(v_1^n) \ne \emptyset\}\mathbf{1}\{\nu_2^{-1}(v_2^n) \ne \emptyset\} \Big),
\end{aligned}
$$

where the last inequality follows from

$$
P_{\text{code}}(v_1^n, v_2^n|u^n, \nu_1, \nu_2) \le \mathbf{1}\{\nu_1^{-1}(v_1^n) \ne \emptyset\}\mathbf{1}\{\nu_2^{-1}(v_2^n) \ne \emptyset\}.
$$

From the proof of Lemma 8 we have

$$
\sum_{\nu_1} P(\nu_1|u^n)\mathbf{1}\{\nu_1^{-1}(v_1^n) \ne \emptyset\} \le 2^{nC_{1d}}P(v_1^n|u^n).
$$

In addition, we have

$$
\begin{aligned}
&\sum_{\nu_2} P_{\text{code}}(\nu_2, y^n|u^n)\mathbf{1}\{\nu_2^{-1}(v_2^n) \ne \emptyset\} \\
&\quad = \mathbf{P}\left\{ \exists z : V_2^n(z) = v_2^n, Y^n = y^n | U^n = u^n \right\} \\
&\quad \le \sum_{z=1}^{2^{nC_{2d}}} \mathbf{P}\left\{ V_2^n(z) = v_2^n, Y^n = y^n | U^n = u^n \right\} \\
&\quad = 2^{nC_{2d}} P_{\text{code}}(v_2^n, y^n|u^n),
\end{aligned}
$$

where the inequality follows from the union bound. Thus

$$
2^{n(C_{1d}+C_{2d})}P(v_1^n|u^n)P_{\text{code}}(v_2^n, y^n|u^n)
$$

is an upper bound for the sum in Equation (15). We can now bound the sum in Equation (14) from above by

$$\begin{aligned}&2^{n(C_{1d}+C_{2d})}\\ &\quad\times \sum_{A_\epsilon^{(n)}} P_{\text{code}}(u^n, v_2^n, y^n) P(v_1^n|u^n) P(x_1^n, x_2^n|u^n, v_1^n, v_2^n)\\ &\quad\leq 2^{n(\zeta+4\epsilon)} \sum_{A_\epsilon^{(n)}} P_{\text{code}}(u^n,v_2^n,y^n)P(v_1^n,x_1^n,x_2^n|u^n,v_2^n),\end{aligned}$$

where the inequality follows from Lemma 9.

Similar to the notation we used to bound $\mathbf{P}(\mathcal{E}_0)$ and $\mathbf{P}(\mathcal{E}_U)$, we define $A_\epsilon^{(n)}(U,V_2,Y)$ as the typical set with respect to $P(u,v_2,y)$. In addition, for every $(u^n,v_2^n,y^n)\in A_\epsilon^{(n)}(U,V_2,Y)$, we define $A_\epsilon^{(n)}(u^n,v_2^n,y^n)$ as the set of all (v_1^n,x_1^n,x_2^n) such that

$$(u^n,v_1^n,v_2^n,x_1^n,x_2^n,y^n)\in A_\epsilon^{(n)}.$$

Again by Theorem 15.2.2 of [5] we have

$$A_\epsilon^{(n)}(u^n,v_2^n,y^n) \le 2^{n(H(V_1,X_1,X_2|U,V_2,Y)+2\epsilon)}.$$

We can now bound $\mathbf{P}(\mathcal{E}_{V_1})$ from above by

$$\begin{aligned}&2^{n((R_1-C_{10})^+ + (R_2 - C_2^{\text{in}})^+ + \zeta + 4\epsilon)}\\ &\quad\times \sum P_{\text{code}}(u^n,v_2^n,y^n)\sum P(v_1^n,x_1^n,x_2^n|u^n,v_2^n),\end{aligned}$$

where the first sum is over all (u^n,v_2^n,y^n) in $A_\epsilon^{(n)}(U,V_2,Y)$ and the second sum is over all (v_1^n,x_1^n,x_2^n) in $A_\epsilon^{(n)}(u^n,v_2^n,y^n)$. We have

$$\begin{aligned}&\sum_{A_\epsilon^{(n)}(u^n,v_2^n,y^n)} P(v_1^n,x_1^n,x_2^n|u^n,v_2^n)\\ &\quad\le 2^{n(H(V_1,X_1,X_2|U,V_2,Y)+2\epsilon)}2^{-n(H(V_1,X_1,X_2|U,V_2)-2\epsilon)}\\ &\quad= 2^{-n(I(X_1,X_2;Y|U,V_2)-4\epsilon)}.\end{aligned}$$

Thus $\mathbf{P}(\mathcal{E}_{V_1X_2})\to 0$ if

$$(R_1-C_{10})^+ + (R_2-C_2^{\text{in}})^+ < I(X_1,X_2;Y|U,V_2)-\zeta-8\epsilon.$$

Bound on $\mathbf{P}(\mathcal{E}_{V_1})$: When $\mathcal{E}_{V_1}$ occurs,

$$\begin{aligned}&\Big(U^n(w_{10},w_{20}), V_1^n(\hat{w}_{1d},\hat{Z}_1), V_2^n(w_{2d},\hat{Z}_2),\\ &\qquad X_1^n(\hat{w}_{11}|U^n,\hat{V}_1^n), X_2^n(w_{22}|U^n,\hat{V}_2^n), Y^n\Big)\in A_\epsilon^{(n)}\end{aligned}$$

for some $\hat{w}_{1d}\ne w_{1d}$. In this case, $(\hat{V}_1^n,\hat{V}_2^n,\hat{X}_1^n,\hat{X}_2^n)$ and $(V_1^n,V_2^n,X_1^n,X_2^n)$ are independent given $(U^n,V_2^n(.),X_2^n(.))$. Therefore,

$$(\hat{V}_1^n,\hat{V}_2^n,\hat{X}_1^n,\hat{X}_2^n)\to(U^n,V_2^n(.),X_2^n(.))\to Y^n$$

is a Markov chain. Thus we can bound $\mathbf{P}(\mathcal{E}_{V_1})$ from above by

$$\begin{aligned}&2^{n(R_1-C_{10})^+}\sum_{A_\epsilon^{(n)}}\sum_{\nu_2,\chi_2}\Big(P_{\text{code}}(u^n,\nu_2,\chi_2,y^n)\\ &\qquad\qquad\times P_{\text{code}}(v_1^n,v_2^n,x_1^n,x_2^n|u^n,\nu_2,\chi_2)\Big)\end{aligned}$$

We simplify the sum as

$$\begin{aligned}&\sum_{A_\epsilon^{(n)}}\sum_{\nu_2,\chi_2} P_{\text{code}}(u^n,\nu_2,\chi_2,y^n)P_{\text{code}}(v_1^n,v_2^n,x_1^n,x_2^n|u^n,\nu_2,\chi_2)\\ &\quad=\sum_{A_\epsilon^{(n)}}\Big(P(u^n)P(x_1^n|u^n,v_1^n) \qquad (16)\\ &\quad\times\sum_{\nu_2,\chi_2} P_{\text{code}}(\nu_2,\chi_2,y^n|u^n)P_{\text{code}}(v_1^n,v_2^n,x_2^n|u^n,\nu_2,\chi_2)\Big).\end{aligned}$$

Next, we find an upper bound on the inner sum. We have

$$\begin{aligned}&\sum_{\nu_2,\chi_2} P_{\text{code}}(\nu_2,\chi_2,y^n|u^n)P_{\text{code}}(v_1^n,v_2^n,x_2^n|u^n,\nu_2,\chi_2)\\ &\quad=\sum_{\nu_1,\nu_2,\chi_2}\Big(P_{\text{code}}(\nu_2,\chi_2,y^n|u^n)P(\nu_1|u^n)\\ &\qquad\qquad\times P_{\text{code}}(v_1^n,v_2^n,x_2^n|u^n,\nu_1,\nu_2,\chi_2)\Big)\\ &\quad\le\sum_{\nu_1,\nu_2,\chi_2}\Big(P_{\text{code}}(\nu_2,\chi_2,y^n|u^n)P(\nu_1|u^n) \qquad (17)\\ &\quad\times\mathbf{1}\big\{\nu_1^{-1}(v_1^n)\neq\emptyset\big\}\mathbf{1}\big\{\nu_2^{-1}(v_2^n)\cap\chi_2^{-1}(x_2^n)\neq\emptyset\big\}\Big),\end{aligned}$$

where the last inequality follows from

$$\begin{aligned}&P_{\text{code}}(v_1^n,v_2^n,x_2^n|u^n,\nu_1,\nu_2,\chi_2)\\ &\quad\le\mathbf{1}\big\{\nu_1^{-1}(v_1^n)\neq\emptyset\big\}\mathbf{1}\big\{\nu_2^{-1}(v_2^n)\cap\chi_2^{-1}(x_2^n)\neq\emptyset\big\}.\end{aligned}$$

From the proof of Lemma 8, we get

$$\sum_{\nu_1}P(\nu_1|u^n)\mathbf{1}\big\{\nu_1^{-1}(v_1^n)\neq\emptyset\big\}\le 2^{nC_{1d}}P(v_1^n|u^n).$$

In addition,

$$\begin{aligned}&\sum_{\nu_2}P_{\text{code}}(\nu_2,\chi_2,y^n|u^n)\mathbf{1}\big\{\nu_2^{-1}(v_2^n)\cap\chi_2^{-1}(x_2^n)\neq\emptyset\big\}\\ &\quad=\mathbf{P}\left\{\exists z: V_2^n(z)=v_2^n, X_2^n(z)=x_2^n, Y^n=y^n|U^n=u^n\right\}\\ &\quad\le\sum_{z=1}^{2^{nC_{2d}}}\mathbf{P}\left\{V_2^n(z)=v_2^n, X_2^n(z)=x_2^n, Y^n=y^n|U^n=u^n\right\}\\ &\quad=2^{nC_{2d}}P_{\text{code}}(v_2^n,x_2^n,y^n|u^n),\end{aligned}$$

where the inequality follows from the union bound. Thus

$$2^{n(C_{1d}+C_{2d})}P(v_1^n|u^n)P_{\text{code}}(v_2^n,x_2^n,y^n|u^n)$$

is an upper bound for the sum in Equation (17). We can now bound the sum in Equation (16) from above by

$$\begin{aligned}&2^{n(C_{1d}+C_{2d})}\\ &\quad\times\sum_{A_\epsilon^{(n)}}P_{\text{code}}(u^n,v_2^n,x_2^n,y^n)P(v_1^n|u^n)P(x_1^n|u^n,v_1^n)\\ &\quad\le 2^{n(\zeta+4\epsilon)}\sum_{A_\epsilon^{(n)}}P_{\text{code}}(u^n,v_2^n,x_2^n,y^n)P(v_1^n,x_1^n|u^n,v_2^n),\end{aligned}$$

where the inequality follows from Lemma 9.

Finally, we bound $\mathbf{P}(\mathcal{E}_{V_1})$ from above by

$$\begin{aligned}&2^{n((R_1-C_{10})^+ +\zeta+4\epsilon)}\\ &\quad\times\sum P_{\text{code}}(u^n,v_2^n,x_2^n,y^n)\sum P(v_1^n|u^n,v_2^n)P(x_1^n|u^n,v_1^n),\end{aligned}$$

where the first sum is over all (u^n, v_2^n, x_2^n, y^n) in $A_\epsilon^{(n)}(U, V_2, X_2, Y)$ and the second sum is over all (v_1^n, x_1^n) in $A_\epsilon^{(n)}(u^n, v_2^n, x_2^n, y^n)$. We have

$$\begin{aligned}\sum_{A_\epsilon^{(n)}(u^n, v_2^n, x_2^n, y^n)} & P(v_1^n, x_1^n | u^n, v_2^n) \\ & \le 2^{n(H(V_1, X_1|U, V_2, X_2, Y)+2\epsilon)} 2^{-n(H(V_1, X_1|U, V_2)-2\epsilon)} \\ & = 2^{-n(I(X_1;Y|U, V_2, X_2)-4\epsilon)}.\end{aligned}$$

Thus $\mathbf{P}(\mathcal{E}_{V_1}) \to 0$ if

$$(R_1 - C_{10})^+ < I(X_1; Y|U, V_2, X_2) - \zeta - 8\epsilon.$$

Bound on $\mathbf{P}(\mathcal{E}_{V_1V_2})$: The event $\mathcal{E}_{V_1V_2}$ occurs when $(\hat{w}_{10}, \hat{w}_{20}) = (w_{10}, w_{20})$, but $\hat{w}_{1d} \neq w_{1d}$ and $\hat{w}_{2d} \neq w_{2d}$. In this case, Y^n is independent of $(\hat{V}_1^n, \hat{V}_2^n, \hat{X}_1^n, \hat{X}_2^n)$ given U^n. This leads to the upper bound

$$\begin{aligned}& 2^{n((R_1-C_{10})^+ + (R_2-C_{20})^+)} \\ & \qquad \times \sum P_{\text{code}}(u^n, y^n) \sum P_{\text{code}}(v_1^n, v_2^n, x_1^n, x_2^n | u^n)\end{aligned}$$

for $\mathbf{P}(\mathcal{E}_{V_1V_2})$, where the sums are over $A_\epsilon^{(n)}(U, Y)$ and $A_\epsilon^{(n)}(u^n, y^n)$, respectively. By Corollary 10 we have

$$\begin{aligned}\sum_{A_\epsilon^{(n)}(u^n, y^n)} & P_{\text{code}}(v_1^n, v_2^n, x_1^n, x_2^n | u^n) \\ & \le 2^{n(H(V_1, V_2, X_1, X_2|U, Y)+2\epsilon)} \\ & \quad \times 2^{-n(-\zeta + H(V_1, V_2, X_1, X_2|U)-6\epsilon)} \\ & = 2^{-n(I(X_1, X_2;Y|U)-\zeta-8\epsilon)}.\end{aligned}$$

Hence $\mathbf{P}(\mathcal{E}_{V_1V_2})$ goes to zero if

$$(R_1 - C_{10})^+ + (R_2 - C_{20})^+ < I(X_1, X_2; Y|U) - \zeta - 8\epsilon.$$

Bound on $\mathbf{P}(\mathcal{E}_{X_1})$: If $\mathcal{E}_{X_1}$ occurs, then

$$(\hat{w}_{10}, \hat{w}_{20}, \hat{w}_{1d}, \hat{w}_{2d}, \hat{w}_{22}) = (w_{10}, w_{20}, w_{1d}, w_{2d}, w_{22}),$$

but $\hat{w}_{11} \neq w_{11}$ and

$$\left(U^n, V_1^n, V_2^n, \hat{X}_1^n, X_2^n, Y^n\right) \in A_\epsilon^{(n)}.$$

In this case, $\hat{X}_1^n$ and Y^n are independent given $(U^n, V_1^n, V_2^n, X_2^n)$. Thus we can bound $\mathbf{P}(\mathcal{E}_{X_1})$ from above by

$$2^{n(R_1 - C_1^{\text{in}})^+} \sum P_{\text{code}}(u^n, v_1^n, v_2^n, x_2^n, y^n) \sum P(x_1^n | u^n, v_1^n),$$

where the first sum is over $A_\epsilon^{(n)}(U, V_1, V_2, X_2, Y)$ and the second sum is over $A_\epsilon^{(n)}(u^n, v_1^n, v_2^n, x_2^n, y^n)$. Further, we have

$$\sum_{A_\epsilon^{(n)}(u^n, v_1^n, v_2^n, x_2^n, y^n)} P(x_1^n | u^n, v_1^n) \le 2^{-n(I(X_1;Y|U, V_1, V_2, X_2)-4\epsilon)},$$

thus $\mathbf{P}(\mathcal{E}_{X_1}) \to 0$ if

$$(R_1 - C_1^{\text{in}})^+ < I(X_1; Y|U, V_1, V_2, X_2) - 4\epsilon.$$

Bound on $\mathbf{P}(\mathcal{E}_{X_1X_2})$: When $\mathcal{E}_{X_1X_2}$ occurs,

$$(\hat{w}_{10}, \hat{w}_{20}, \hat{w}_{1d}, \hat{w}_{2d}) = (w_{10}, w_{20}, w_{1d}, w_{2d}),$$

but $\hat{w}_{ii} \neq w_{ii}$ for $i = 1, 2$, and

$$\left(U^n, V_1^n, V_2^n, \hat{X}_1^n, \hat{X}_2^n, Y^n\right) \in A_\epsilon^{(n)}.$$

In this case Y^n is independent of $(\hat{X}_1^n, \hat{X}_2^n)$ given (U^n, V_1^n, V_2^n). Thus $\mathbf{P}(\mathcal{E}_{X_1X_2})$ is bounded by

$$\begin{aligned}& 2^{n((R_1-C_1^{\text{in}})^+ + (R_2-C_2^{\text{in}})^+)} \\ & \qquad \times \sum P_{\text{code}}(u^n, v_1^n, v_2^n, y^n) \sum P(x_1^n, x_2^n | u^n, v_1^n, v_2^n)\end{aligned}$$

where the first sum is over $A_\epsilon^{(n)}(U, V_1, V_2, Y)$ and the second sum is over $A_\epsilon^{(n)}(u^n, v_1^n, v_2^n, y^n)$. We have

$$\sum_{A_\epsilon^{(n)}(u^n, v_1^n, v_2^n, y^n)} P(x_1^n, x_2^n | u^n, v_1^n, v_2^n) \le 2^{-n(I(X_1, X_2;Y|U, V_1, V_2)-4\epsilon)},$$

thus $\mathbf{P}(\mathcal{E}_{X_1X_2})$ goes to zero if

$$(R_1 - C_1^{\text{in}})^+ + (R_2 - C_2^{\text{in}})^+ < I(X_1, X_2; Y|U, V_1, V_2) - 4\epsilon.$$

APPENDIX F
THE MUTUAL COVERING LEMMA

In this appendix, we state and prove the mutual covering lemma, which is a variation of a result by the same name in the book by El Gamal and Kim [18]. Our result differs from the result in [18] in two ways. One, our result is stated and proven for weakly typical sets, rather than strongly typical sets, and two, we require complete independence rather than pairwise independence between codewords.

Lemma 11 (Mutual Covering Lemma)**.** *Let U, V_1, and V_2 be random variables jointly distributed as $P(u, v_1, v_2)$. Suppose $\mathcal{A}$ and $\mathcal{B}$ are finite sets with $|\mathcal{A}| \ge 2^{nr_1}$ and $|\mathcal{B}| \ge 2^{nr_2}$. Given $U^n = u^n$, for every $(a, b) \in \mathcal{A} \times \mathcal{B}$, let $V_1^n(a)$ and $V_2^n(b)$ be random vectors generated in an i.i.d. manner according to the distributions*

$$\mathbf{P}\left\{V_1^n(a) = v_1^n | U^n = u^n\right\} = \prod_{t=1}^{n} P(v_{1t}|u_t)$$

$$\mathbf{P}\left\{V_2^n(b) = v_2^n | U^n = u^n\right\} = \prod_{t=1}^{n} P(v_{2t}|u_t),$$

where $P(v_1|u)$ and $P(v_2|u)$ are the marginals of $P(v_1, v_2|u)$. Then

$$\lim_{n\to\infty} \mathbf{P}\left\{\exists (a, b) \in \mathcal{A} \times \mathcal{B} : (U^n, V_1^n(a), V_2^n(b)) \in A_\delta^{(n)}\right\} = 1$$

if $r_1 + r_2 > I(V_1; V_2|U) + 4\delta$.

Our proof, which is given in detail at the end of this appendix, follows the achievability proof of the rate-distortion theorem given in [5, pp. 318-324].

The next corollary follows from Lemma 9 in Appendix E and is the conditional version of Lemma 10.5.2 of [5].

Corollary 12. *For every $(u^n, v_1^n, v_2^n) \in A_\delta^{(n)}$,*

$$P(v_2^n|u^n) \ge P(v_2^n|u^n, v_1^n) 2^{-n(I(V_1;V_2|U)+4\delta)}.$$

We next prove the Mutual Covering Lemma. It suffices to show

$$\lim_{n\to\infty} \mathbf{P}\left\{\forall (a, b) \in \mathcal{A} \times \mathcal{B} : (U^n, V_1^n(a), V_2^n(b)) \notin A_\delta^{(n)}\right\} = 0.$$

For every (u^n, v_1^n, v_2^n), define

$$K(u^n, v_1^n, v_2^n) = \begin{cases} 1 & \text{if } (u^n, v_1^n, v_2^n) \in A_\delta^{(n)}, \\ 0 & \text{otherwise.} \end{cases}$$

Then we have

$$\begin{aligned}
&\mathbf{P}\left\{\forall (a,b) \in \mathcal{A} \times \mathcal{B} : (U^n, V_1^n(a), V_2^n(b)) \notin A_\delta^{(n)}\right\} \\
&\quad = \sum_{u^n} P(u^n) \Big[1 - \sum_{v_1^n, v_2^n} \Big(K(u^n, v_1^n, v_2^n) \\
&\qquad\qquad\qquad \times P(v_1^n|u^n) P(v_2^n|u^n)\Big)\Big]^{|\mathcal{A}||\mathcal{B}|} \\
&\quad \le \sum_{u^n} P(u^n) \Big[1 - 2^{-n(I(V_1;V_2|U)+4\delta)} \sum_{v_1^n, v_2^n} \Big(K(u^n, v_1^n, v_2^n) \\
&\qquad\qquad\qquad \times P(v_1^n|u^n) P(v_2^n|u^n, v_1^n)\Big)\Big]^{|\mathcal{A}||\mathcal{B}|} \qquad (18)
\end{aligned}$$

where the inequality follows by Corollary 12. By Lemma 10.5.3 of [5], which states that for $x, y \in [0,1]$ and positive n,

$$(1 - xy)^n \le 1 - x + e^{-yn},$$

the right hand side of Equation (18) can be bounded from above by

$$\begin{aligned}
&\sum_{u^n} P(u^n) \Big[1 - \sum_{v_1^n, v_2^n} K(u^n, v_1^n, v_2^n) P(v_1^n, v_2^n|u^n) \\
&\qquad + \exp\big(-|\mathcal{A}||\mathcal{B}| 2^{-n(I(V_1;V_2|U)+4\delta)}\big)\Big] \\
&\quad \le 1 - \sum_{u^n, v_1^n, v_2^n} K(u^n, v_1^n, v_2^n) P(u^n, v_1^n, v_2^n) \\
&\qquad + \exp\big(-2^{n(r_1+r_2-I(V_1;V_2|U)-4\delta)}\big) \\
&\quad = \mathbf{P}\left\{(U^n, V_1^n, V_2^n) \notin A_\delta^{(n)}\right\} \\
&\qquad + \exp\big(-2^{n(r_1+r_2-I(V_1;V_2|U)-4\delta)}\big)
\end{aligned}$$

which goes to zero as $n \to \infty$ provided $r_1 + r_2 > I(V_1;V_2|U) + 4\delta$.

APPENDIX G
PROOF OF THEOREM 4

Note that if (S,T) is a jointly Gaussian random pair with correlation matrix

$$\Sigma_{ST} = \begin{pmatrix} \sigma_S^2 & \rho\sigma_S\sigma_T \\ \rho\sigma_S\sigma_T & \sigma_T^2 \end{pmatrix},$$

then by Theorem 8.4.1 of [5],

$$\begin{aligned}
H(S,T) &= \frac{1}{2}\log\left|2\pi e \Sigma_{ST}\right| \\
&= \frac{1}{2}\log\Big((2\pi e)^2(1-\rho^2)\sigma_S^2\sigma_T^2\Big) \qquad (19)
\end{aligned}$$

and

$$\begin{aligned}
H(S|T) &= H(S,T) - H(T) \\
&= \frac{1}{2}\log\Big((2\pi e)(1-\rho^2)\sigma_S^2\Big). \qquad (20)
\end{aligned}$$

Choose (C_{10}, C_{20}) and $(\rho_0, \rho_{10}, \rho_{20}, \rho_{1d}, \rho_{2d})$ such that the constraints of Theorem 4 are satisfied. Then choose U, (V_1, V_2), and (X_1', X_2') independently according to the distributions $U \sim \mathcal{N}(0,1)$, $(V_1, V_2) \sim \mathcal{N}(\mathbf{0}, \Sigma)$, and $(X_1', X_2') \sim \mathcal{N}(\mathbf{0}, \mathrm{I}_2)$, where

$$\Sigma = \begin{pmatrix} 1 & \rho_0 \\ \rho_0 & 1 \end{pmatrix}$$

and I_2 is the 2×2 identity matrix. Then

$$I(V_1;V_2|U) = I(V_1;V_2) = \frac{1}{2}\log\frac{1}{1-\rho_0^2}.$$

Next, for $i = 1, 2$, define

$$\frac{1}{\sqrt{P_i}} X_i = \rho_{i0} U + \rho_{id} V_i + \rho_{ii} X_i'.$$

Note that by Equation (7), this definition results in $\mathbb{E}[X_i^2] = P_i$ for $i = 1, 2$. Since $Y = X_1 + X_2 + Z$,

$$\begin{aligned}
Y = (\rho_{10}\sqrt{P_1} + \rho_{20}\sqrt{P_2})U + \rho_{1d}\sqrt{P_1}V_1 + \rho_{2d}\sqrt{P_2}V_2 \\
+ \rho_{11}\sqrt{P_1}X_1' + \rho_{22}\sqrt{P_2}X_2' + Z.
\end{aligned}$$

Next, we use Equations (19) and (20) to calculate the bounds in Theorem 2, to obtain Theorem 4. In the calculations that follow let $\{i,j\} = \{1,2\}$. We have

$$\begin{aligned}
I(X_i;Y|U,V_1,V_2,X_j) &= H(Y|U,V_1,V_2,X_j) - H(Y|X_1,X_2) \\
&= H(\rho_{ii}\sqrt{P_i}X_i' + Z) - H(Z) \\
&= \frac{1}{2}\log(1 + \rho_{ii}^2\gamma_i).
\end{aligned}$$

Next we calculate

$$\begin{aligned}
&I(X_1,X_2;Y|U,V_1,V_2) \\
&\quad = H(Y|U,V_1,V_2) - H(Y|X_1,X_2) \\
&\quad = H(\rho_{11}\sqrt{P_1}X_1' + \rho_{22}\sqrt{P_2}X_2' + Z) - H(Z) \\
&\quad = \frac{1}{2}\log(1 + \rho_{11}^2\gamma_1 + \rho_{22}^2\gamma_2).
\end{aligned}$$

Unlike the above calculations, for which we only required Equation (19), in the calculation of the next two mutual information terms we require Equation (20), since the random variables which appear in the corresponding conditional entropies are dependent. We have

$$\begin{aligned}
&I(X_i;Y|U,V_j,X_j) \\
&\quad = H(Y|U,V_j,X_j) - H(Y|X_1,X_2) \\
&\quad = H\big(\rho_{id}\sqrt{P_i}V_i + \rho_{ii}\sqrt{P_i}X_i' + Z|V_j\big) - H(Z) \\
&\quad = \frac{1}{2}\log\big(1 + (\rho_{id}^2 + \rho_{ii}^2)\gamma_i\big)\Big(1 - \frac{\rho_0^2\rho_{id}^2\gamma_1}{1 + (\rho_{id}^2 + \rho_{ii}^2)\gamma_i}\Big) \\
&\quad = \frac{1}{2}\log(1 + \tilde{\rho}_{ii}^2\gamma_i)
\end{aligned}$$

and

$$\begin{aligned}
&I(X_1, X_2; Y|U, V_i)\\
&\quad = H(Y|U, V_i) - H(Y|X_1, X_2)\\
&\quad = H\big(\rho_{jd}\sqrt{P_j}V_j + \rho_{11}\sqrt{P_1}X_1' + \rho_{22}\sqrt{P_2}X_2' + Z|V_i\big)\\
&\qquad - H(Z)\\
&\quad = \frac{1}{2}\log\bigg[\big(1 + \rho_{ii}^2\gamma_i + (1-\rho_{j0}^2)\gamma_j\big)\\
&\qquad\qquad \times\Big(1 - \frac{\rho_0^2\rho_{jd}^2\gamma_j}{1 + \rho_{ii}^2\gamma_i + (1-\rho_{j0}^2)\gamma_j}\Big)\bigg]\\
&\quad = \frac{1}{2}\log(1 + \rho_{ii}^2\gamma_i + \tilde{\rho}_{jj}^2\gamma_j).
\end{aligned}$$

For the final two remaining expressions, we have

$$\begin{aligned}
I(X_1, X_2; Y|U) &= H(Y|U) - H(Z)\\
&= \frac{1}{2}\log\big(1 + (1-\rho_{10}^2)\gamma_1 + (1-\rho_{20}^2)\gamma_2\\
&\qquad + 2\rho_0\rho_{1d}\rho_{2d}\bar{\gamma}\big)
\end{aligned}$$

and

$$\begin{aligned}
I(X_1, X_2; Y) &= H(Y) - H(Z)\\
&= \frac{1}{2}\log\big(1 + \gamma_1 + \gamma_2 + 2(\rho_{10}\rho_{20} + \rho_0\rho_{1d}\rho_{2d})\bar{\gamma}\big),
\end{aligned}$$

where $\bar{\gamma} = \sqrt{\gamma_1\gamma_2}$.

REFERENCES

[1] P. Noorzad, M. Effros, M. Langberg, and T. Ho, "On the power of cooperation: Can a little help a lot?" in *Proc. IEEE Int. Symp. Information Theory*, 2014.

[2] T. Ho, M. Effros, and S. Jalali, "On equivalence between network topologies," in *Proc. Allerton Conf. Communication, Control, and Computing*, 2010.

[3] S. Jalali, M. Effros, and T. Ho, "On the impact of a single edge on the network coding capacity," in *Information Theory and Applications Workshop*, 2011.

[4] F. M. J. Willems, "The discrete memoryless multiple access channel with partially cooperating encoders," *IEEE Trans. Inf. Theory*, vol. IT-29, no. 3, pp. 441–445, 1983.

[5] T. M. Cover and J. A. Thomas, *Elements of Information Theory*, 2nd ed. Wiley, 2006.

[6] K. Marton, "A coding theorem for the discrete memoryless broadcast channel," *IEEE Trans. Inf. Theory*, vol. IT-25, no. 3, pp. 306–311, 1979.

[7] A. El Gamal and E. C. van der Meulen, "A proof of Marton's coding theorem for the discrete memoryless broadcast channel," *IEEE Trans. Inf. Theory*, vol. IT-27, no. 1, pp. 120–122, 1981.

[8] R. Ahlswede, "Multi-way communication channels," in *Proc. Int. Symp. Information Theory*, 1971.

[9] ——, "The capacity region of a channel with two senders and two receivers," *Ann. Prob.*, vol. 2, pp. 805–814, 1974.

[10] H. Liao, "Multiple access channels," Ph.D. dissertation, Dept. Elect. Eng., Univ. Hawaii, 1972.

[11] M. A. Wigger, "Cooperation on the multiple-access channel," Ph.D. dissertation, ETH Zurich, September 2008.

[12] R. Schneider, *Convex Bodies: The Brunn-Minkowski Theory*. Cambridge University Press, 1993.

[13] T. M. Cover, A. El Gamal, and M. Salehi, "Multiple access channels with arbitrary correlated sources," *IEEE Trans. Inf. Theory*, vol. IT-26, no. 6, pp. 648–657, 1980.

[14] A. Dembo and O. Zeitouni, *Large Deviations Techniques and Applications*, 2nd ed. Springer-Verlag, 1998.

[15] A. D. Wyner, "Recent results in the Shannon theory," *IEEE Trans. Inf. Theory*, vol. IT-20, no. 1, pp. 2–10, 1974.

[16] T. M. Cover, "Some advances in broadcast channels," Stanford University - Department of Statistics, Tech. Rep. 9, September 1974.

[17] D. Slepian and J. K. Wolf, "A coding theorem for multiple access channels with correlated sources," *Bell Syst. Tech. J.*, vol. 52, no. 7, pp. 1037–1076, 1973.

[18] A. El Gamal and Y.-H. Kim, *Network Information Theory*, 2nd ed. Cambridge University Press, 2012.